

UNCLASSIFIED



# **z/OS SRRAUDIT Dialog Management Procedures**

**Version 6, Release 53**

**27 January 2022**

**Developed by DISA for the DoD**

UNCLASSIFIED

TABLE OF CONTENTS

	<b>Page</b>
Initial Setup .....	1
For Sites That Run the SRRAUDIT Process .....	1
For Sites That Do Not Run the SRRAUDIT Process .....	2
Main Menu Panel .....	3
Authorized User Groups: Pre-Populate and Edit .....	4
For Sites That Run the SRRAUDIT Process .....	4
For Sites That Do Not Run the SRRAUDIT Process .....	4
Browse List of All Userids.....	6
Enter Selection Choices for Pre-Population.....	7
Enter Selection Choices for Pre-Population Help.....	10
Verify and Update Authorized User Groups.....	11
Update User PROC EXAMRPTS.....	13
Review Reports for Findings, User Access, and Dataset Rules.....	14
Review Open / Not Reviewed PDI Finding Reports .....	15
Browse Current User Access Lists.....	16
Browse Dataset SENSITIVE Reports.....	17
Edit Started Task List.....	18
Verify and Update Authorized User Groups.....	19
Asset Definition Process .....	21
Asset Definition Process Help .....	22
Product List .....	24
Dataset Help Panel .....	29
Compuware Abend-AID Panels.....	31
BMC CONTROL-D Panels .....	35
BMC CONTROL-M Panels.....	40
BMC CONTROL-O Panels .....	46
BMC CONTROL-M/Restart Panels .....	50
BMC INCONTROL (IOA) Panels .....	53
BMC MAINVIEW for z/OS Panels.....	58
CA AUDITOR (CA EXAMINE).....	66
CA MICS Resource Management.....	68
CA MIM Panels .....	70
Catalog Solution Panels .....	73
CA1 Panels.....	75
CA Common Services (CCS) Panels.....	81
CICS Panels .....	83
CL/SuperSession Panels .....	90
IBM Comm Server File Transfer Protocol (CSFTP) Panels.....	94
IBM Comm Server Simple Mail Transfer Protocol (CSSMTP) Panels .....	95
IBM Comm Server TCP/IP (CSTCP) Panels.....	96
IBM Comm Server TN3270E Telnet Server (CSTNT) Panels.....	97
FDR Panels .....	98
FEP Panels .....	100
IBM Hardware Configuration Definition (HCD) Panels.....	101
IBM Health Checker .....	103

IBM Integrated Crypto Service Facility (ICSF) Panels .....105  
MQSeries/Websphere MQ Panels.....109  
NC-PASS Panels.....111  
Tivoli Netview Panels .....114  
CA ROSCOE Panels .....119  
SDSF Panels.....126  
SRRAUDIT Panels .....128  
Tivoli Asset Discovery for z/OS (TADz) Panels .....130  
Transparent Data Migration Facility (TDMF) Panels.....133  
Vanguard Security Solutions (VSS) Panels .....134  
VTAM Panels .....136  
CA VTAPE Panels.....138  
HTTP/Web Application Server Panels .....142  
Vulnerability Questions .....143

**Summary of Changes**

<b>Revision Number</b>	<b>Document Revised</b>	<b>Description of Change</b>	<b>Release Date</b>
V6R49	V6R48 (22 Jan 2021)	Removed Product STC data set panel for CSSMTP.	25 April 2021
V6R34	V6R33 (27 Oct 2017)	No changes to this document.	17 November 2017
V6R33	V6R32 (28 July 2017)	Added Product STC data set panel for CSSMTP.	27 October 2017
V6R28	V6R27 (22 April 2016)	Changed Vulnerability Questions to remove AAMV0016 request and add request for information to ACP00270.	28 October 2016

## Initial Setup

### For Sites That Run the SRRAUDIT Process

**Modify:** EXAMRPTS member in the SYS3.SRRAUDIT.CNTL, changing the following variables to refer to the correct data set names:

```
CNTL=SYS2.SRRAUDIT.CNTL
CAILIB=SYS2A.EXAMINE.CAILIB
CAICLIB=SYS2.EXAMINE.CAICLIB
CAIISPP=SYS2.EXAMINE.CAIISPP
CAIISPM=SYS2.EXAMINE.CAIISPM
CAIISPT=SYS2.EXAMINE.CAIISPT
CAIDBS1=SYS3.EXAMINE.CAIDBS1
CAIDBS2=SYS2.EXAMINE.CAIDBS2
```

**Note:** The above changes can be performed by starting the Dialog process and at the Application Option Menu selecting option [B](#).

The Initial Setup messages and prompts appear only once during a TSO session. If the user enters this process and logs off of TSO and later logs on to TSO, the information will be requested again.

**START:** At the ISPF Option 6, type the following on the command line and press "Enter":

```
EXEC 'SYS2.SRRAUDIT.CNTL(SRR$TSO)'
```

You will receive the following panel prompts:

```
----- Security Readiness Review Self-Audit -----
SRR$TSO                                DIALOG Setup

The current system install library high level qualifier is:
  SYS2.SRRAUDIT

Type new HLQ: _____

The current user library high level qualifier is:
  SYS3.SRRAUDIT

Type new HLQ: _____

EXIT (PF3) To end.                      Press Enter to use current high-level qualifiers
```

**Note:** Use the defaults for each of the system install and user libraries. Press "Enter" to proceed to [SRR\\$MAIN](#).

**For Sites That Do Not Run the SRRAUDIT Process**

**Note:** After uploading and creating the SYS3.FSO.xxxx.mmmyyyy.CNTL data set, the following steps can be performed. The high-level qualifier can be changed below.

**Modify:** EXAMRPTS member in the SYS3.FSO.xxxx.mmmyyyy.CNTL, changing the following variables to refer to the correct data set names:

```
CNTL=SYS2.SRRAUDIT.CNTL - Change to SYS3.FSO.xxxx.mmmyyyy.CNTL
CAILIB=SYS2A.EXAMINE.CAILIB
CAICLIB=SYS2.EXAMINE.CAICLIB
CAIISPP=SYS2.EXAMINE.CAIISPP
CAIISPM=SYS2.EXAMINE.CAIISPM
CAIISPT=SYS2.EXAMINE.CAIISPT
CAIDBS1=SYS3.EXAMINE.CAIDBS1
CAIDBS2=SYS2.EXAMINE.CAIDBS2
```

**Note:** The above changes can be performed by starting the Dialog process and at the Application Option Menu selecting option [B](#).

The Initial Setup messages and prompts appear only once during a TSO session. If the user enters this process and logs off of TSO and later logs on to TSO, the information will be requested again.

**START:** At the ISPF Option 6, type the following on the command line and press "Enter":

```
EXEC 'SYS3.FSO.xxxx.mmmyyyy.CNTL(SRR$TSO)'
```

You will receive the following panel prompts:

```
----- Security Readiness Review Self-Audit -----
SRR$TSO                                DIALOG Setup

The current system install library high level qualifier is:
  SYS2.SRRAUDIT

Type new HLQ: _____

The current user library high level qualifier is:
  SYS3.SRRAUDIT

Type new HLQ: _____

EXIT (PF3) To end.                      Press Enter to use current high-level qualifiers
```

**Note:** Ensure that both high-level qualifiers are changed to SYS3.FSO.xxxx.mmmyyyy or specify the correct high-level qualifiers for each of the system install and user libraries. Press the "Enter" key and proceed to [SRR\\$MAIN](#).

### Main Menu Panel

The following is the main menu. All panels from this point on will contain the Version/Release of the SRRAUDIT process using v.rr as the format (e.g., 6.12).

```

----- Security Readiness Review Self-Audit -----
                          Application option menu
SRR$MAIN                               Version: v.rr
Option ==>

      A - Authorized User Groups: Pre-Populate and Edit
      B - Update User PROC EXAMRPTS
      C - Review reports for Findings, User access & Dataset rules
      D - Products
      E - Vulnerability Questions

EXIT (PF3) To end.

```

The following table describes each option available for the Dialog primary screen:

Option	Description
<a href="#">A</a>	Will display Review System Users and Provide Input to Pre-Population panel.
<a href="#">B</a>	Will edit the SYS3.FSO.xxxx.mmmyyyy.CNTL(EXAMRPTS) or SYS3.SRRAUDIT.CNTL(EXAMRPTS) member (review and/or update Proc JCL).
<a href="#">C</a>	Will display Administration Option Menu panel.
<a href="#">D</a>	Will display the Product List panel.
<a href="#">E</a>	Will display the Vulnerability Questions panel.
Exit/PF3	Exit Dialog process.

## Authorized User Groups: Pre-Populate and Edit

Instructions on this page can be bypassed if the site has collected information from a previous run of the jobs and the collection of information that is contained within the Dialog data set. It is recommended that sites proceed to [Verify and Update Authorized User Groups](#) to update the Dialog User Groups. The following job must be run prior to initiating the Pre-Population process.

### For Sites That Run the SRRAUDIT Process

**Modify:** CACJ051D member in the SYS3.SRRAUDIT.CNTL, customizing the Job card, ensuring that the USER=SRRAUDT is removed or replaced. If SYS3.SRRAUDIT.DATA data set exists, delete all of the JCL for the DATA DD statement in Step JSTEP010.

**Submit:** CACJ051D member in the SYS3.SRRAUDIT.CNTL after the above changes are completed. Upon successful completion of CACJ051D, proceed with the following steps to initiate the dialog process.

If Step JSTEP020 returns a non-zero return code, review the contents of SYS3.SRRAUDIT.LISTUSER for error messages.

### For Sites That Do Not Run the SRRAUDIT Process

**Modify:** CACJ051D member in the SYS3.FSO.*xxxx.mmmyyyy*.CNTL, customizing the Job card, ensuring that the USER=SRRAUDT is removed or replaced. Change the following variables to reference a high-level data set qualifier:

```
// SET SRRINST=SYS2.SRRAUDIT  
// SET SRRUSER=SYS3.SRRAUDIT
```

Both variables can specify the same high-level data set qualifier as shown in the following statements:

```
// SET SRRINST=SYS3.FSO.xxxx.mmmyyyy  
// SET SRRUSER=SYS3.FSO.xxxx.mmmyyyy
```

If SYS3.FSO.*xxxx.mmmyyyy*.DATA data set exists, delete all of the JCL for the DATA DD statement in step JSTEP010.

**Submit:** CACJ051D member in the SYS3.FSO.*xxxx.mmmyyyy*.CNTL after the above changes are completed. Upon successful completion of CACJ051D, proceed with the following steps to initiate the dialog process.

If Step JSTEP020 returns a non-zero return code, review the contents of SYS3.FSO.*xxxx.mmmyyyy*.LISTUSER for error messages.



Upon completion of the above Job, start the Dialog process as specified in section [Initial Setup](#). After selecting Option A, the following screen will appear.

```

----- Security Readiness Review Self-Audit -----
          Review Authorized Users and Provide Input to Pre-Population
SRR$AUGR                                     Version: v.rr
Option ===>

          A - Browse list of all userids

          B - Enter selection choices for Pre-Population

          C - Verify and update Authorized user groups

The accuracy/validity of the user groups is the
primary responsibility of the site SA.  Pre-population
Is only intended to populate the user groups based on
Best Available Input Data and is never guaranteed to be
100 percent accurate.

EXIT (PF3) to end.

```

The following table describes each option available for the Dialog primary screen:

Option	Description
<a href="#">A</a>	This option will browse the list of all userids. This is a member created by the CACJ051D Job.
<a href="#">B</a>	Enter selections for the authorized user pre-selection process.
<a href="#">C</a>	Verify and/or Update Authorized User Groups, this is also noted as the Authorized users list.
<a href="#">Exit/PF3</a>	Return to Application Option Menu.

**Browse List of All Userids**

Select Option A. This option will browse the ALLUSERS member in the Dialog data set.

The following is a sample of what the browse of ALLUSERS may look like. The information displayed below may be different depending on the ACP and the users defined to the system.

BROWSE	SYS3.SRRAUDIT.DATA (ALLUSERS)	Line	00000000	Col	001	080
Command	====>			Scroll	====>	CSR
***** Top of Data *****						
AA1GATE	ECSGATE V6	FJB	STC	AA1GATE	STC	
AA1GATE	ECSGATE V6	ACS (STC)	CIC (FJB)	M-UID (FJB	STC)	
ABENDAID	ABEND-AID / MVS	FJB	STC	ABENDAID	STC	
ABENDAID	ABEND-AID / MVS	ACS (STC)	CIC (FJB)	M-UID (FJB	STC)	
ACFBKAL	ACF2 BACKUP #2	FJB	STC	ACFBKAL	MAINT	STC
ACFBKAL	ACF2 BACKUP #2	ACS (STC)	CIC (FJB)	M-UID (FJB	STC)	
ACFBKUP	ACF2 BACKUP STC	FJB	STC	ACFBKUP	PPGM	STC
ACFBKUP	ACF2 BACKUP STC	ACS (STC)	CIC (FJB)	M-UID (FJB	STC)	
ACF2	ACF2	FJB	STC	ACF2	STC	
ACF2	ACF2	ACS (STC)	CIC (FJB)	M-UID (FJB	STC)	
ACTCIT03	STCID FOR CICS	FJB	STC	ACTCIT03	CICS	JOBFROM MUSASS
ACTCIT03	STCID FOR CICS	NO-SMC	STC			
ACTCIT03	STCID FOR CICS	ACS (STC)	CIC (FJB)	M-UID (FJB	STC)	
AESCMDS	CLEVER/TCPIP STC	FJB	STC	AESCMDS	STC	
AESCMDS	CLEVER/TCPIP STC	ACS (STC)	CIC (FJB)	M-UID (FJB	STC)	
AESNETS	CLEVER/TCPIP STC	FJB	STC	AESNETS	STC	
AESNETS	CLEVER/TCPIP STC	ACS (STC)	CIC (FJB)	M-UID (FJB	STC)	
AESTCPIP	CLEVER/TCPIP STC	FJB	STC	AESTCPIP	STC	
AESTCPIP	CLEVER/TCPIP STC	ACS (STC)	CIC (FJB)	M-UID (FJB	STC)	

Option	Description
<a href="#">Exit/PF3</a>	Return to Review System Users and Provide Input to Pre-Population Menu.

### Enter Selection Choices for Pre-Population

**Note:** Pre-population of the Dialog information was done as a result of requests of all sites present at the TIM. This process in many cases populates the member with unauthorized users and can miss other authorized users. It is the Site's responsibility to edit and update each member in the dialog data set to verify that the information is accurate. Please maintain the accuracy of this data by removing any unauthorized users and adding any missing authorized users.

```

----- Security Readiness Review Self-Audit -- Row 1 to 44 of 44
              Pre-Populate Authorized User Groups
SRR$POP                                           Version: v.rr
Command ==> _____ Scroll ==> CSR

HELP  (PF1) For additional information.          EXIT  (PF3) To end.

Prefix  Group Description
-----
APPBAUDT Application Production Batch Userids.
APPDAUDT Application Development Programmers.
APPSAUDT Application Production Support Team members.
AUDTAUDT Auditors whether they are System, Security, or other
AUTOAUDT Automated Operation STCs/Batch Jobs
BMCADMIN INCONTROL Admins/Owners of CONTROL-D/M/O.
BMCUSER  INCONTROL Users of CONTROL-D/M/O.
CHGOWNER Users authorized to issue the chown in UNIX.
CICBAUDT CICS Batch Programs.
CICDAUDT CICS Developers.
CICSAUDT CICS Started Task.
CICSDEF  CICS regions default user ids (DFLTUSER).
CICUAUDT CICS Utils (CONTROLO, BatIDs via CONTROLM, MAINVIEW)
CONSOLES The System Console user ids
DABAAUDT Data Base Administrators
DAEMAUDT Unix Daemon user ids
DASBAUDT DASD batch, jobs that perform DASD Backups, Migrate
DASDAUDT DASD Administrators
DPCSAUDT Decentralized Prod Cntl and Sched personnel
DUMPAUDT STCs/Batch ids that perform Dump processing

```

EMERAUDT	Emergency TSO logon ids
FTPUSER	FTP only process/server to server userids
MICSADM	MICS Administrators
MICSUSER	MICS End Users
MQSAAUDT	MQ Series Administrators
MQSDAUDT	Decentralized MQ Series Administrators
MVREAD	Mainview users that require read only mode.
MVUPDT	Mainview users that require some update functions.
OMVSAUDT	The OMVS started task kernel
OPERAUDT	Operations personnel
PARMSTC	Users that have READ access justification via IAO.
PCSPAUDT	Production Control and Scheduling personnel
PRODAUDT	Production Started Tasks and batch logon ids
SECAAUDT	Security Administrators
SECBAUDT	Security batch, jobs that perform ACP maintenance
SECDAUDT	Decentralized Security Administrators
SERVAUDT	Unix Server user ids
SMFBAUDT	STCs/BATCH ids that perform SMF dump processing
STCGAUDT	STCs ids, that perform GTF processing
SUPRAUDT	User ids that require BPX.SUPERUSER
SYSCAUDT	CICS Systems Programmers.
SYSPAUDT	Systems Programmers or Systems Administrators
TAPEAUDT	Tape Librarians, CA1 Prod Batch Jobs, and CA1 STCs.
***** Bottom of data *****	

This Screen or Panel gives the System SRRAUDIT Auditor a selection for seven options per line. If no selections are made on this screen, no users will be selected for the User Group.

Press "Enter" to process the entered selections and return to the SRR\$AUGR screen.

<b>Option</b>	<b>Description</b>
Enter	Process selection items for each group of users; return to current menu selection.
<a href="#">Help/PF1</a>	Displays the help panel for this process.
<a href="#">Exit/PF3</a>	Return to Review System Users and Provide Input to Pre-Population Menu.

### Enter Selection Choices for Pre-Population Help

The following continuous screen will be displayed.

```

----- Security Readiness Review Self-Audit -----
                Pre-Populate Authorized User Groups
SRR$POP                                           Version: v.rr

ENTER  To scroll forward.   PF3   To Exit/Return.
PF11  To scroll forward.   PF10  To scroll backward.

Help documentation to create site Authorized User Groups

More:      +

For RACF:
Enter a Group name or Attribute in the input fields.
At least one field must be entered to generate a group list.
Entering an attribute will also select group level attributes.
    Example: SPECIAL will select SPECIAL and GSPECIAL.

For Top Secret:
Enter a Profile name or Attribute in the input fields.
At least one field must be entered to generate a group list.

For ACF2:
Enter a Privilege name in the input fields.
At least one field must be entered to generate a group list.

The process:
The program will search the User list and add the ID to the
    Authorized group if a match is found.

A Group or Profile name can be a partial name.
    Example: Entering 'STC' will select groups STC, STCOMVS and WEBSTC.

The program can be run multiple times to create missing groups or to replace
    an existing group.

At least one field must be entered to generate a group list.

End of document.

```

Option	Description
<a href="#">Exit/PF3</a>	Return to Review System Users and Provide Input to Pre-Population Menu.

### Verify and Update Authorized User Groups

To verify and update the authorized user groups, perform the following steps:

Select Option C. The following screen will appear:

```

----- Security Readiness Review Self-Audit -- Row 1 to 44 of 44
              Verify and update Authorized user groups
SRR$USR                                     Version: v.rr
Command ==>>                               Scroll ==>> CSR

View or Update the Authorized user groups
Line Commands:
S or B for Browse | E for Edit | V for View                                     Status
=====
_ APPBAUDT  Application Production Batch Userids.                               Empty
_ APPDAUDT  Application Development Programmers.                               Empty
_ APPSAUDT  Application Production Support Team members.
_ AUDTAUDT  Auditors whether they are System, Security, or other
_ AUTOAUDT  Automated Operation STCs/Batch Jobs
_ BMCADMIN  INCONTROL Admins/Owners of CONTROL-D/M/O.
_ BMCUSER   INCONTROL Users of CONTROL-D/M/O.
_ CHGOWNER  Users authorized to issue the chown in UNIX.                       Empty
_ CICBAUDT  CICS Batch Programs.                                               Empty
_ CICDAUDT  CICS Developers.                                                   Empty
_ CICSAUDT  CICS Started Task.                                                 Empty
_ CICSDEF   CICS regions default user ids (DFLTUSER).                         Empty
_ CICUAUDT  CICS Utils (CONTROL0, BatIDs via CONTROLM, MAINVIEW)               Empty
_ CONSOLES  The System Console user ids
_ DABAAUDT  Data Base Administrators
_ DAEMAUDT  Unix Daemon user ids
_ DASBAUDT  DASD batch, jobs that perform DASD Backups, Migrate
_ DASDAUDT  DASD Administrators
_ DPCSAUDT  Decentralized Prod Cntl and Sched personnel                         Empty
_ DUMPAUDT  STCs/Batch ids that perform Dump processing
_ EMERAUDT  Emergency TSO logon ids
_ FTPUSER   FTP only interactive users                                         Empty
_ MICSADM   MICS Administrators                                                 Empty
_ MICSUSER  MICS End Users                                                      Empty
_ MQSAAUDT  MQ Series Administrators
_ MQSDAUDT  Decentralized MQ Series Administrators                             Empty
_ MVREAD    Mainview users that require read only mode.                       Empty
_ MVUPDT    Mainview users that require some update functions.                 Empty
_ OMVSAUDT  The OMVS started task kernel
_ OPERAUDT  Operations personnel
_ PARMSTC   Users that have READ access justification via IAO.                 Empty
_ PCSPAUDT  Production Control and Scheduling personnel                       Empty
_ PRODAUDT  Production Started Tasks and batch logon ids
_ SECAAUDT  Security Administrators
_ SECBAUDT  Security batch, jobs that perform ACP maintenance
_ SECDAUDT  Decentralized Security Administrators                             Empty
_ SERVAUDT  Unix Server user ids
_ SMFBAUDT  STCs/BATCH ids that perform SMF dump processing
_ STCGAUDT  STCs ids, that perform GTF processing
_ SUPRAUDT  User ids that require BPX.SUPERUSER
_ SYSCAUDT  CICS Systems Programmers.                                           Empty
_ SYSPAUDT  Systems Programmers or Systems Administrators

```

```

_ TAPEAUDT   Tape Librarians, CA1 Prod Batch Jobs, and CA1 STCs.
_ TSTCAUDT   Trusted Started Tasks users
_ WEBAAUDT   Web Server Administrators
***** Bottom of data *****

```

With this screen, you may browse (B or S), update/edit (E), or view (V) the Authorized User groups. The Status column specifies whether the group exists in the Dialog data set. If the group does not exist, the Empty message appears in the Status column. Entries with the Status of "Empty" will have to be edited to add users for that group.

Option	Description
Enter	Refresh panel list.
<a href="#">Exit/PF3</a>	Return to Review System Users and Provide Input to Pre-Population Menu.

Member Option	Description
B/S	Browse Selected member.
E	Edit Selected member.
V	View Selected member.



### Update User PROC EXAMRPTS

Select Option **B**. This option will edit the EXAMRPTS member in the CNTL data set.

The following is a sample of what the edit of EXAMRPTS may look like:

```

EDIT          SYS3.SRRAUDIT.CNTL(EXAMRPTS) - 01.10          Columns 00001
00080
Command ==>                                           Scroll ==>
CSR
***** Top of Data
*****
000001 //EXAMRPTS PROC CNTL=SYS2.SRRAUDIT.CNTL,
000002 //          CAILIB=SYS2A.EXAMINE.CAILIB,
000003 //          CAICLIB=SYS2.EXAMINE.CAICLIB,
000004 //          CAIISPP=SYS2.EXAMINE.CAIISPP,
000005 //          CAIISPM=SYS2.EXAMINE.CAIISPM,
000006 //          CAIISPT=SYS2.EXAMINE.CAIISPT,
000007 //          CAIDBS1=SYS3.EXAMINE.CAIDBS1,          USER PROFILE DATA SET
000008 //          CAIDBS2=SYS2.EXAMINE.CAIDBS2
000009 //*****
000010 //*
000011 //* THIS PROC SHOULD ONLY BE CHANGED IN THE SYS3 USER LIBRARY
000012 //* EXECUTE BATCH TSO WITH LIBRARIES FOR CA-EXAMINE
000013 //*
000014 //* 12/13/2004 JL.NELSON CHANGED BLKSIZE FOR LARGE LIBRARIES
000015 //* 04/25/2005 JL.NELSON CHANGED CAIDBS1 TO SYS3 PER GARRY SETTIMI
000016 //* 09/20/2005 JL.NELSON CHANGED REGION=0M,TIME=MAXIMUM
000017 //* 03/01/2006 JL.NELSON CHGED BLKSIZE Z/OS 1.7 IEC141I 013-E1,IFG0196L
000018 //*****
000019 //*
000020 //PSTEP020 EXEC  PGM=IKJEFT01,REGION=0M,TIME=MAXIMUM
000021 //*

```

Option	Description
<a href="#">End</a>	Return to Application Option Menu.
Save	Saves EXAMRPTS member.
<a href="#">Cancel</a>	Return to Application Option Menu.
<a href="#">Exit/PF3</a>	Return to Application Option Menu.

### Review Reports for Findings, User Access, and Dataset Rules

This selection will display the Administration Option menu. This selection will provide information from information that has been processed during the SRRAUDIT process or the SRR review.

```

----- Security Readiness Review Self-Audit -----
                    Administration option menu
SRR$ADMN                                     Version: v.rr
Option ==>

      A - Review open PDI finding reports
      B - Browse current User access lists
      C - Browse data set SENSITIVE reports
      D - Edit STARTED TASK list
      E - Verify and update Authorized user groups
      F - Asset Definition Process

EXIT (PF3) to end.

```

Option	Description
<a href="#">A</a>	Review a list of PDI members that are determined to be Open findings.
<a href="#">B</a>	Browse a list of Authorized users; the members identify the data set grouping of the users.
<a href="#">C</a>	Browse a list of Sensitive report members. The members contain all details on the access for the group.
<a href="#">D</a>	Edit the Started Task member in the CNTL data set.
<a href="#">E</a>	Verify and Update Authorized user groups.
<a href="#">F</a>	Create the Asset Definition of the system.
<a href="#">Exit/PF3</a>	Return to Application Option Menu.

**Review Open / Not Reviewed PDI Finding Reports**

This option will list any and all open PDI findings that were discovered during the SRRAUDIT process or an SRR Review.

Select Option A. The following is an example of a possible screen display:

```

----- Security Readiness Review Self-Audit -- Row 1 to 18 of 113
              Open PDI / Not Reviewed Finding Reports
SRR$PDI
Command ==>> _____ Version: v.rr
                               Scroll ==>> CSR

Review Open and Not Reviewed Potential Discrepancy Items (PDI)s
Line Commands:
S or B for Browse | E for Edit | V for View          Report date 2018/08/10
=====
_ AAMV0040  O   The following inaccessible APF-authorized library(ies) exist
_ AAMV0060  NR  The annual review of APF-authorized libraries is not being p
_ AAMV0350  O   The following non-existent or inaccessible LINKLIST library(
_ ACP00010  O   The following data set access authorization(s) is (are) inap
_ ACP00020  O   The following data set access authorization(s) is (are) inap
_ ACP00030  O   The following data set access authorization(s) is (are) inap
_ ACP00040  O   The following data set access authorization(s) is (are) inap
_ ACP00050  O   The following data set access authorization(s) is (are) inap
_ ACP00060  O   The following data set access authorization(s) is (are) inap
_ ACP00062  O   The following data set access authorization(s) is (are) inap
_ ACP00070  O   The following data set access authorization(s) is (are) inap
_ ACP00080  O   The following data set access authorization(s) is (are) inap
_ ACP00110  O   The following data set access authorization(s) is (are) inap
_ ACP00120  O   The following data set access authorization(s) is (are) inap
_ ACP00130  O   The following data set access authorization(s) is (are) inap
_ ACP00135  O   The following data set access authorization(s) is (are) inap
_ ACP00140  O   The following data set access authorization(s) is (are) inap
_ ACP00150  O   The following data set access authorization(s) is (are) inap

```

With this screen, you may browse (S or B), update/edit (E), or view (V) the open PDI findings.

Option	Description
Enter	Refresh panel list.
<a href="#">Exit/PF3</a>	Return to Administration Option Menu.

Member Option	Description
B/S	Browse Selected member.
E	Edit Selected member.

**Browse Current User Access Lists**

This option will list members that contain the authorized users for the data sets these members represent. This data set was created during the SRRAUDIT process or an SRR Review.

Select Option **B**. The following is an example of a possible screen display:

BROWSE SYS3.SRRAUDIT.CARJ043R.AUACCESS						Row 00001 of 00090
Command ==>						Scroll ==> CSR
Name	Prompt	Size	Created	Changed	ID	
. ACPRPT		67	2015/05/19	2015/05/19 07:24:55	SRRAUDT	
. ACP00260		35	2015/05/19	2015/05/19 07:26:34	SRRAUDT	
. ACP00270		38	2015/05/19	2015/05/19 07:26:43	SRRAUDT	
. ACP00282		70	2015/05/19	2015/05/19 07:30:20	SRRAUDT	
. ACP00293		53	2015/05/19	2015/05/19 07:42:53	SRRAUDT	
. ACP00350		43	2015/05/19	2015/05/19 07:30:59	SRRAUDT	
. ADTRPT		65	2015/05/19	2015/05/19 07:25:17	SRRAUDT	
. ADTUSER		65	2015/05/19	2015/05/19 07:25:15	SRRAUDT	
. APFXRPT		54	2015/05/19	2015/05/19 07:24:34	SRRAUDT	
. BKUPRPT		57	2015/05/19	2015/05/19 07:24:53	SRRAUDT	
. CATMRPT		54	2015/05/19	2015/05/19 07:24:43	SRRAUDT	
. CATURPT		54	2015/05/19	2015/05/19 07:24:45	SRRAUDT	
. CA1PROD		54	2015/05/19	2015/05/19 07:25:05	SRRAUDT	
. CA1RPT		73	2015/05/19	2015/05/19 07:25:07	SRRAUDT	
. CCSRPT		54	2015/05/19	2015/05/19 07:26:22	SRRAUDT	
. CTDRPT		68	2015/05/19	2015/05/19 07:25:56	SRRAUDT	
. CTDSTC		68	2015/05/19	2015/05/19 07:25:54	SRRAUDT	
. CTDUSER		68	2015/05/19	2015/05/19 07:25:51	SRRAUDT	
. CTMJCL		80	2015/05/19	2015/05/19 07:25:59	SRRAUDT	
. CTMRPT		80	2015/05/19	2015/05/19 07:26:11	SRRAUDT	
. CTMSTC		80	2015/05/19	2015/05/19 07:26:07	SRRAUDT	

Option	Description
Enter	Refresh panel list.
<a href="#">Exit/PF3</a>	Return to Administration Option Menu.

Member Option	Description
B/S	Browse Selected member.

**Browse Dataset SENSITIVE Reports**

This option will list members that contain the complete report for each of the sensitive report groupings. This data set was created during the SRRAUDIT process or an SRR Review.

Select Option C. The following is an example of a possible screen display:

```

BROWSE      SYS3.SRRAUDIT.CARJ043R.SENSITVE.RPT          Row 00001 of 00101
Command ====>                                         Scroll ====> CSR
  Name      Prompt          Size    Created          Changed          ID
.  ACPRPT
.  ACP00260
.  ACP00270
.  ACP00282
.  ACP00293
.  ACP00350
.  ADTRPT
.  ADTUSER
.  APFTRPT
.  APFXRPT
.  BKUPRPT
.  CATMRPT
.  CATURPT
.  CA1PROD
.  CA1RPT
.  CCSRPT
.  CICSRPT
.  CICSSTC
.  CTDRPT
.  CTDSTC
.  CTDUSER

```

Option	Description
Enter	Refresh panel list.
<a href="#">Exit/PF3</a>	Return to Administration Option Menu.

Member Option	Description
B/S	Browse Selected member.

**Edit Started Task List**

This process is used to edit the STCILIST member, which is the started task list.

Select Option **D**. The following is an example of a possible screen display:

```

EDIT          SYS3.SRRAUDIT.CNTL(STCILIST) - 01.49          Columns 00001
00080
Command ==>                                          Scroll ==>
CSR
***** Top of Data
*****
000001 * STARTED TASK LIST -
000002 * -----
000003 * DESCRIPTION
000004 * This table is used to match Started Task names to Group IDs. Each
000005 * Group ID is associated with a single PDI.
000006 *
000007 * SSO CHANGE LOG
000008 * 03/14/2005 JL.Nelson Changed for old table.
000009 * 03/02/2006 C. Stern Changed documentation.
000010 * 04/17/2006 C. Fenton Removed DFHSM entries, id is for SMS.
000011 * 05/10/2006 HC - Changed documentation.
000012 * 08/23/2006 HC - Removed ENF per FSO Guidance...see 27JUN06 email
000013 * from Charles.
000014 * 07/31/2007 CF - Removed PDI entries.
000015 * 08/08/2008 CF - Added additional STCs and rearranged identifiers.
000016 *
000017 * SITE CHANGE INSTRUCTIONS
000018 * 1. This table contains entries for Started Proc Names used in this
000019 * release of SRRAUDIT for PDI checking. Procs not contained in
000020 * the list below, example BMCVIEW, are not used in this release
000021 * and should not be added.
000022 * 2. Each site should look at this list, specifically the STC/JOB and

```

Option	Description
<a href="#">End</a>	Return to Administration Option Menu
Save	Saves STCILIST member
<a href="#">Cancel</a>	Return to Administration Option Menu
<a href="#">Exit/PF3</a>	Return to Administration Option Menu

Scroll through member and make changes as needed.

**Verify and Update Authorized User Groups**

To verify and update the authorized user groups, perform the following steps:

Select Option E. The following screen will appear:

```

----- Security Readiness Review Self-Audit -- Row 1 to 50 of 50
              Verify and update Authorized user groups
SRR$USR                                     Version: v.rr
Command ==>                               Scroll ==> CSR

View or Update the Authorized user groups
Line Commands:
S or B for Browse | E for Edit | V for View                                     Status
=====
_ APPBAUDT  Application Production Batch Userids.                               Empty
_ APPDAUDT  Application Development Programmers.                               Empty
_ APPSAUDT  Application Production Support Team members.
_ AUDTAUDT  Auditors whether they are System, Security, or other
_ AUTOAUDT  Automated Operation STCs/Batch Jobs
_ BMCADMIN  INCONTROL Admins/Owners of CONTROL-D/M/O.
_ BMCUSER   INCONTROL Users of CONTROL-D/M/O.
_ CHGOWNER  Users authorized to issue the chown in UNIX.                       Empty
_ CICBAUDT  CICS Batch Programs.                                               Empty
_ CICDAUDT  CICS Developers.                                                    Empty
_ CICSAUDT  CICS Started Task.                                                  Empty
_ CICSDEF   CICS regions default user ids (DFLTUSER).                          Empty
_ CICUAUDT  CICS Utils (CONTROLO, BatIDs via CONTROLM, MAINVIEW)               Empty
_ CONSOLES  The System Console user ids
_ DABAAUDT  Data Base Administrators
_ DAEMAUDT  Unix Daemon user ids
_ DASBAUDT  DASD batch, jobs that perform DASD Backups, Migrate
_ DASDAUDT  DASD Administrators
_ DPCSAUDT  Decentralized Prod Cntl and Sched personnel                         Empty
_ DUMPAUDT  STCs/Batch ids that perform Dump processing
_ EMERAUDT  Emergency TSO logon ids
_ FTPUSERS  FTP only interactive users                                         Empty
_ IOABAUDT  IOA batch users for operations                                     Empty
_ MCATBAT   Batch users requiring ALTER access to Master Catalog               Empty
_ MICSADM   MICS Administrators                                                 Empty
_ MICSUSER  MICS End Users                                                       Empty
_ MQSAAUDT  MQ Series Administrators
_ MQSDAUDT  Decentralized MQ Series Administrators                             Empty
_ MVREAD    Mainview users that require read only mode.                       Empty
_ MVUPDT    Mainview users that require some update functions.                 Empty
_ OMVSAUDT  The OMVS started task kernel
_ OPERAUDT  Operations personnel
_ PARMSTC   Users that have READ access justification via IAO.                 Empty
_ PCSPAUDT  Production Control and Scheduling personnel                         Empty
_ PRODAUDT  Production Started Tasks and batch logon ids
_ ROSCAUTH  ROSCOE Master and Maintenance IDs
_ SECAAUDT  Security Administrators
_ SECBAUDT  Security batch, jobs that perform ACP maintenance
_ SECDAUDT  Decentralized Security Administrators                             Empty
_ SERVAUDT  Unix Server user ids
_ SMFBAUDT  STCs/BATCH ids that perform SMF dump processing
_ STCGAUDT  STCs ids, that perform GTF processing

```

_ SUPRAUDT	User ids that require BPX.SUPERUSER	
_ SYSCAUDT	CICS Systems Programmers.	Empty
_ SYSPAUDT	Systems Programmers or Systems Administrators	
_ TAPDAUDT	Decentralized Tape Librarians.	Empty
_ TAPEAUDT	Tape Librarians, CA1 Prod Batch Jobs, and CA1 STCs.	
_ TSTCAUDT	Trusted Started Tasks users	
_ UPRVAUDT	Users that require specific UNIXPRIV resources	
_ WEBAAUDT	Web Server Administrators	
***** Bottom of data *****		

With this screen, you may browse (S or B), update/edit (E), or view (V) the Authorized User groups. The Status column specifies whether the group exists in the Dialog data set. If the group does not exist, the Error message appears in the Status column. The above has examples of this issue when all entries in the Pre-Population Process have been specified.

Option	Description
Enter	Refresh panel list.
<a href="#">Exit/PF3</a>	Return to Administration Option Menu.

Member Option	Description
B/S	Browse Selected member.
E	Edit Selected member.



**Asset Definition Process**

This function is used to create and/or display the Asset Definition collected for a system.

Select Option F. The following is an example of a possible screen display:

```

----- Security Readiness Review Self-Audit -----
                        Asset Definition Process
SRR$ADMN                                     Version: v.rr
Option ==>> _____

                        Key Fields for Asset Definition Process.
Host Name: TEST.DISA.MIL                     OS390 Sys ID: TEST
Operating System: z/OS                       ACP: RACF
Optional key field, the first 4 IP addresses, if available, are shown.
    127.0.0.1

                        Additional Fields for Asset Definition Process.
Description:      SSOPAC19 Base/test
Classification:  2      MAC:                2      Confidentiality: 2
Status:          1      Use:                3
Building:        xxxx
Room:            _____
Serial Number:   xxxxxxxxxxxxxx
Barcode:         _____
Make:           _____
Model:          xxxxxxxxxxxxxx
Manufacturer:    xxxxxxxxxxxxxx

EXIT (PF3) to end with no action.      CREATE to create asset file.
SAVE to save above information.

```

If the Host Name and/or IP addresses fields are blank, ensure the user running this process has a valid OMVS segment and home directory is defined to the system. Fields below the **Additional Fields for Asset Definition Process** are the only input fields besides Option on this screen. The following fields must have a value entered for the **CREATE** or **SAVE** options:

- Classification – 0 - Secret, 1 - Confidential, or 2 - Unclassified
- MAC – 0 - MAC I, 1 - MAC II, 2 - MAC III
- Confidentiality – 1 - Public, 2 - Sensitive, 3 - Confidential
- Status – 1 - Online, 2 - Offline
- Use – 1 - Production, 2 - Support, 3 - Test/Development

Option	Description
Create	This option will create the XMLASSET data set and save the asset information in the Dialog data set.
Save	This option will save the asset information in the Dialog data set.
<a href="#">Help</a>	Help for the Create Asset Definition process.
<a href="#">Exit/PF3</a>	Return to Administration Option Menu.

## Asset Definition Process Help

After the XMLASSET data set is created, follow the instruction specified in the **Download Created Asset and Importing Created Asset** steps in this help screen.

```

----- Security Readiness Review Self-Audit -----
                          Asset Definition Process
SRR$ADMN                                     Version: v.rr

ENTER  To scroll forward.   PF3   To Exit/Return.
PF11   To scroll forward.   PF10  To scroll backward.

More:   - +

This Help is used to create a sites asset import file for the web based
application that tracks asset vulnerabilities.

Asset Information:

The Key Fields and Optional key entries are collected from information
available on the system. The Additional fields can be filled in by the
System/Security Administrator. This panel will require that the following
fields be specified:

    Classification, MAC, Confidentiality, Status, and Use.

These fields require that specific values be specified. The following is a
list of the fields and the only values available:

Classification:  0 - Secret, 1 - Confidential, or 2 - Unclassified
MAC:             0 - MAC I, 1 - MAC II, 2 - MAC III
Confidentiality: 1 - Public, 2 - Sensitive, 3 - Confidential
Status:         1 - Online, 2 - Offline
Use:           1 - Production, 2 - Support, 3 - Test/Development

Commands Available for this process:

END      - Escape process without creating or saving any information.
CREATE   - With the information provided, creates the Asset Definition
          dataset and saves the information that is entered on the screen.
SAVE     - Saves the information that is entered on the screen only.

Downloading Created Asset:

The file created in this process can be downloaded and imported into the
application that tracks asset vulnerabilities. Use the following steps for
downloading:

1. At the TSO ready prompt or the ISPF option 6.
2. Initiate the File Transfer Process to transfer from host to PC.
   (Receive Files From Host)
3. Enter the file CREATED in this process in the Host-File Name enclosed
   in quotes. (e.g. 'SYS3.FSO.MMD.XMLASSET')
4. Enter a file name, with an xml extension in the PC-File Name.
   (e.g. d:\asset.xml)
5. Select Text for the Transfer Mode.
6. Under Options, specify ASCII only, over ASCII CRLF.
7. Save information and initiate the download process.

Importing Created Asset Definition:

```

The file created in this process after downloading, the file saved in 4. above can be imported into the application that tracks asset vulnerabilities. Use the following steps for downloading:

To be determined at a future date.

End of document.

<b>Option</b>	<b>Description</b>
<a href="#">Exit/PF3</a>	Return to Asset Definition Process.

### Product List

This function is used to identify the products that are available on the system. The information collected about a product will be used in the automation of the vulnerabilities for the product.

```

SRRPPROD ----- Security Readiness Review Self-Audit - Row 1 to 37 of 37
                                Product List
SRRMPROD                                Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
  Line Commands:
  Y Used  N Unused  S Used and Select for Additional Information
=====
  Product  U Description                                Condition
- ABNDAID  Compuware Abend-Aid                        Used?
- BMCCTD   BMC CONTROL-D                               Used?
- BMCCTM   BMC CONTROL-M                               Used?
- BMCCTO   BMC CONTROL-O                               Used?
- BMCCTR   BMC CONTROL-M/Restart                     Used?
- BMCIOA   BMC INCONTROL (IOA)                       Used?
- BMCMVZ   BMC MAINVIEW for z/OS                     Used?
- CAAUDTR  CA AUDITOR (CA EXAMINE)                   Used?
- CAMICS   CA MICS Resource Management               Used?
- CAMIM    CA MIM Resource Sharing for z/OS           Used?
- CATSOL   Catalog Solutions                         Used?
- CA1      CA1 Tape Management System                 Used?
- CCS      CA Common Services (CCS)                   Used?
- CICS     CICS Transaction Server                    Used?
- CLSUPER  CL/SuperSession                            Used?
- CSFTP    IBM Comm Server File Transfer Protocol (CSFTP)  Used?
- CSSMTP   IBM Comm Server Simple Mail Transfer Protocol (CSSMTP)  Used?
- CSTCP    IBM Comm Server TCP/IP (CSTCP)              Used?
- CSTNT    IBM Comm Server TN3270E Telnet Server (CSTNT)  Used?
- FDR      FDR                                         Used?
- FEP      Front End Processor                          Used?
- HCD      IBM Hardware Configuration Definition (HCD)    Used?
- HLTHCK   IBM Health Checker                            Used?
- ICSF     IBM Integrated Crypto Service Facility (ICSF)   Used?
- MQS      MQSeries/Websphere MQ                         Used?
- NCPASS   NC-PASS                                       Used?
- NETVIEW  Tivoli Netview                                  Used?
- ROSCOE   CA ROSCOE                                       Used?
- SDSF     System Display and Search Facility                 Used?
- SRRAUDT  SRRAUDIT Process                                  Used?
- TADZ     Tivoli Asset Discovery for z/OS (TADz)              Used?
- TDMF     Transparent Data Migration Facility (TDMF)      Used?
- VSS      Vanguard Security Solutions (VSS)             Used?
- VTAM     Y VTAM                                           Missing
- VTAPE    CA VTAPE                                       Used?
- WAS      HTTP/Web Application Server                    Used?
***** Bottom of data *****

```

The Condition indicates the status of the product. "Used?" is an indicator that the product has not been identified as being installed or not installed on the system. "Missing" is an indicator that additional information is required for the product.

Option	Description
<a href="#">Cancel</a>	Return to Application Option Menu without Saving information.
<a href="#">End/Exit/PF3</a>	Save information and return to Application Option Menu.
Enter	Refresh panel list.

Line Option	Description
N	Specifies that the Product is not available on the system.
Y	Specifies that the Product is available on the system.
S	Specifies that the Product is available on the system and proceed to additional screens.

At this screen, you can specify (N, Y, or S) on a product line. Specify (N) to indicate that the product is not available on the system. Specify (Y) to indicate that the product is available on the system. Specifying (Y) may produce a **Missing** condition that is resolved by specifying (S). Specify (S) to indicate that the product is available on the system. Specifying (S) will in most cases produce additional panels requesting specific information about the product.

#### An explanation of the Dataset Panel names:

Product Install Data Sets	Would normally have WRITE and/or greater access given to the System Programming staff.
Product STC Data Sets	Would normally have WRITE and/or greater access given to the Products Started Task userid or the Products batch userid as well as the System Programming staff.
Product User Data Sets	Would normally have WRITE and/or greater access given to specific groups of userids or all userids as well as the System Programming staff.
All Product Data Sets	Would normally have WRITE and/or greater access given to the System Programming staff but may have other user access requirements.

The following table identifies the additional panels that appear for possible request for information when specifying (S) for a product:

Product	Title	Panels
ABNDAID	Compuware Abend-Aid	<a href="#">STC JCL Location</a> <a href="#">Product Install Data Sets</a> <a href="#">Product STC Data Sets</a> <a href="#">Product User Data Sets</a>
BMCCTD	BMC CONTROL-D	<a href="#">STC JCL Location</a> <a href="#">Configuration Location</a> <a href="#">Product Install Data Sets</a> <a href="#">Product STC Data Sets</a> <a href="#">Product User Data Sets</a>
BMCCTM	BMC CONTROL-M	<a href="#">STC JCL Location</a> <a href="#">Configuration Location</a> <a href="#">Product Install Data Sets</a> <a href="#">Product STC Data Sets</a> <a href="#">Product User Data Sets</a>

## UNCLASSIFIED

Product	Title	Panels
		<a href="#">User/Application JCL Data Sets</a>
BMCCTO	BMC CONTROL-O	<a href="#">STC JCL Location</a> <a href="#">Configuration Location</a> <a href="#">Product Install Data Sets</a> <a href="#">Product STC Data Sets</a>
BMCCTR	BMC CONTROL-M/Restart	<a href="#">STC JCL Location</a> <a href="#">Product Install Data Sets</a> <a href="#">Product User Data Sets</a>
BMCIOA	BMC INCONTROL (IOA)	<a href="#">STC JCL Location</a> <a href="#">Configuration Location</a> <a href="#">Product Install Data Sets</a> <a href="#">Product STC Data Sets</a> <a href="#">Product User Data Sets</a>
BMCMVZ	BMC MAINVIEW for z/OS	<a href="#">Subsystem Identifier</a> <a href="#">STC JCL Location</a> <a href="#">Resource Panel</a> <a href="#">Configuration Location</a> <a href="#">Product Install Data Sets</a> <a href="#">Product STC Data Sets</a>
CAAUDTR	CA AUDITOR (CA EXAMINE)	<a href="#">Product Install Data Sets</a> <a href="#">Product User Data Sets</a>
CAMICS	CA MICS	<a href="#">Product Install Data Sets</a> <a href="#">Product User Data Sets</a>
CAMIM	CA MIM Resource Sharing for z/OS	<a href="#">STC JCL Location</a> <a href="#">Product Install Data Sets</a> <a href="#">Product STC Data Sets</a>
CATSOL	Catalog Solutions	<a href="#">Product Loadlib Data Sets</a> <a href="#">Product Install Data Sets</a>
CA1	CA1 Tape Management System	<a href="#">STC JCL Location</a> <a href="#">Module Location</a> <a href="#">Configuration Location</a> <a href="#">Product Install Data Sets</a> <a href="#">Product STC Data Sets</a> <a href="#">Other Data Sets</a>
CCS	CA Common Services (CCS)	<a href="#">STC JCL Location</a> <a href="#">Product Install Data Sets</a>
CICS	CICS Transaction Server	<a href="#">STC JCL Location</a> <a href="#">Module Location</a> <a href="#">Resource Identification</a> <a href="#">Product Install Data Sets</a> <a href="#">Product STC Data Sets</a>
CLSUPER	CL/SuperSession	<a href="#">STC JCL Location</a> <a href="#">Configuration Settings</a> <a href="#">Product Install Data Sets</a> <a href="#">Product STC Data Sets</a>

## UNCLASSIFIED

Product	Title	Panels
CSFTP	IBM Comm Server File Transfer Protocol (CSFTP)	<a href="#">STC JCL Location</a>
CSSMTP	IBM Comm Server Simple Mail Transfer Protocol (CSSMTP)	<a href="#">STC JCL Location</a>
CSTCP	IBM Comm Server TCP/IP (CSTCP)	<a href="#">STC JCL Location</a>
CSTNT	IBM Comm Server TN3270E Telnet Server (CSTNT)	<a href="#">STC JCL Location</a>
FDR	Fast Dump Restore (FDR)	<a href="#">Module Location</a> <a href="#">Product Install Data Sets</a>
FEP	Front End Processor	<a href="#">All Product Data Sets</a>
HCD	IBM Hardware Configuration Definition (HCD)	<a href="#">Product Install Data Sets</a> <a href="#">Product User Data Sets</a>
HLTHCK	IBM Health Checker	<a href="#">STC JCL Location</a> <a href="#">Product STC Data Sets</a>
ICSF	IBM Integrated Crypto Service Facility (ICSF)	<a href="#">STC JCL Location</a> <a href="#">Configuration Location</a> <a href="#">Product Install Data Sets</a> <a href="#">Product STC Data Sets</a>
MQS	MQSeries/Websphere MQ	<a href="#">Subsystem Identifier</a> <a href="#">STC JCL Location</a>
NCPASS	NC-PASS	<a href="#">STC JCL Location</a> <a href="#">Product Install Data Sets</a> <a href="#">Product STC Data Sets</a>
NETVIEW	Tivoli Netview	<a href="#">STC JCL Location</a> <a href="#">Configuration Location</a> <a href="#">Keyword and Value</a> <a href="#">Product Install Data Sets</a> <a href="#">Product STC Data Sets</a>
ROSCOE	CA ROSCOE	<a href="#">STC JCL Location</a> <a href="#">Resource Panel</a> <a href="#">Configuration Location</a> <a href="#">Product Install Data Sets</a> <a href="#">Product STC Data Sets</a>
SDSF	System Display and Search Facility	<a href="#">STC JCL Location</a> <a href="#">Product Install Data Sets</a>
SRRAUDT	SRRAUDIT Process	<a href="#">Product Install Data Sets</a> <a href="#">Product User Data Sets</a>
TADZ	Tivoli Asset Discovery for z/OS (TADz)	<a href="#">STC/Batch JCL Location</a> <a href="#">Product Install Data Sets</a> <a href="#">Product STC Data Sets</a>
TDMF	Transparent Data Migration Facility (TDMF)	<a href="#">All Product Data Sets</a>
VSS	Vanguard Security Solutions (VSS)	<a href="#">Product Install Data Sets</a> <a href="#">Product User Data Sets</a>
VTAM	VTAM	<a href="#">STC JCL Location</a> <a href="#">All Product Data Sets</a>
VTAPE	CA VTAPE	<a href="#">Subsystem Identifier</a> <a href="#">STC JCL Location</a> <a href="#">Product Install Data Sets</a>

**UNCLASSIFIED**

---

<b>Product</b>	<b>Title</b>	<b>Panels</b>
		<a href="#">Product STC Data Sets</a>
WAS	HTTP/Web Application Server	<a href="#">STC JCL Location</a>



## Dataset Help Panel

The following help can be used to assist sites in obtaining a list of data sets for requested Products and Vulnerability Questions. Dataset prefixes can be specified that do not obtain a data set list. An example is specifying **SYS2.SRRAUDIT.V**, which will not populate data set panel with any additional data sets. However, during evaluation, this will review all data set rules that use **SYS2.SRRAUDIT.V**.

```

----- Security Readiness Review Self-Audit -----
                Entering Data Sets and/or Data Set Mask/Prefix Help
SRRMPROD                                           Version: v.rr

ENTER  To scroll forward.   PF3   To Exit/Return.
PF11   To scroll forward.   PF10  To scroll backward.

                                           More:      +

Typing over a current data set line.

1.  Current line before overtyping.

_  SYS2.TEST.DATA.SET.NAME _____

2.  Current line after overtyping.

_  SYS2.TESTING.DATASET.NAME _____

3.  Lines after pressing enter key.

_  SYS2.TEST.DATA.SET.NAME _____
_  SYS2.TESTING.DATASET.NAME _____

How to enter the data sets and/or data set mask/prefix.

1.  Specifying a data set name.

_  SYS2.TEST.DATA.SET.NAME _____

    The above data set must be unique to return a specific data set.

2.  Specifying a data set mask, use one of the following examples.

_  SYS2.*.CAILIB _____

    The above will return all data sets with the first qualifier
    of SYS2 and a third qualifier of CAILIB upon pressing the enter
    key. The resulting list will contain data set with three or more
    qualifiers.

_  SYS2.CA1 _____

    The above will return all data sets that begin with SYS2.CA1 as
    the first and second qualifiers. This will not retrieve
    SYS2.CA1ABA.DATASET, for the second qualifier is not CA1. To
    obtain this data set specify SYS2.CA1* in the above prompt.

3.  Specifying a data set prefix, use the following examples.

_  SYS2.CA1. _____

```

**UNCLASSIFIED**

The above will not return any data sets. It can be used as a place holder for several data sets. Remember the period '.' at the end of the prefix. Also, do not specify this with any sort of mask. (example: SYS3.CA1.V\*.)

<b>Option</b>	<b>Description</b>
Exit/PF3	Return to any of the many data set request panels.

### Compuware Abend-AID Panels

#### STC JCL Location

The following panel appears for Compuware Abend-Aid. Specify the member and data set location of each Compuware Abend-Aid Product STC and/or Batch job on this system. The data set can specify the actual or an alias of the data set.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
                          Compuware Abend-AID
SRRMPROD                                     Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
              EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the Userid of the STCs or batch jobs for this product.
  Enter the members and data sets that contain the JCL for this product.
=====
  UserId      Member      Data set that contains the member JCL
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Product Install data sets.
Enter	Refresh panel list.

Return to [Product List table](#).

### Product Install Data Sets

The following panel appears for any product that requests a list of data sets for the product. Specify the actual or alias of the data set or specify the data set prefix or data set mask. If data set prefixes or data set masks are used, ensure that any data sets not associated with the product are deleted.

```

----- Security Readiness Review Self-Audit ---- Row 1 to 1 of 1
                    Compuware Abend-AID
SRRMPROD                                     Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the data sets and/or data set mask/prefix of the product installation
  data sets.
=====
  Data set names and/or Data set prefixes          Volume
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Product STC data sets.
Enter	Refresh panel list.
<a href="#">Help/PF1</a>	Display data set names and/or data set Prefixes Help.

Return to [Product List table](#).

### Product STC Data Sets

The following panel appears for any product that requests a list of data sets for the product. Specify the actual or alias of the data set or specify the data set prefix or data set mask. If data set prefixes or data set masks are used, ensure that any data sets not associated with the product are deleted. The data sets, data set prefixes, or data set masks specified in this panel may require that the Products Started Task has WRITE and/or greater access.

```

----- Security Readiness Review Self-Audit ---- Row 1 to 1 of 1
                          Compuware Abend-AID
SRRMPROD                                     Version: v.rr
Command ==>>> _____ Scroll ==>>> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the data sets and/or data set mask/prefix of the product STC
  data sets.
=====
  Data set names and/or Data set prefixes          Volume
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Product User data sets.
Enter	Refresh panel list.
<a href="#">Help/PF1</a>	Display data set names and/or data set Prefixes Help.

Return to [Product List table](#).

### Product User Data Sets

The following panel appears for any product that requests a list of data sets for the product. Specify the actual or alias of the data set or specify the data set prefix or data set mask. If ,data set prefixes or data set masks are used, ensure that any data sets not associated with the product are deleted. The data sets to be specified are the Region Dump data sets, the Report databases, and Source listing files/source listing shared directories.

```

----- Security Readiness Review Self-Audit ---- Row 1 to 1 of 1
                          Compuware Abend-AID
SRRMPROD                                     Version: v.rr
Command ==>>> _____ Scroll ==>>> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the data sets and/or data set mask/prefix of the product user
  data sets.
=====
  Data set names and/or Data set prefixes          Volume
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and return to Product List.
Enter	Refresh panel list.
<a href="#">Help/PF1</a>	Display data set names and/or data set Prefixes Help.

Return to [Product List table](#).

### BMC CONTROL-D Panels

#### STC JCL Location

The following panel appears for BMC CONTROL-D. Specify the member and data set location of each BMC CONTROL-D Product STC and/or Batch job on this system. The data set can specify the actual or an alias of the data set.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
                        BMC CONTROL-D
SRRMPROD                                     Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the Userid of the STCs or batch jobs for this product.
  Enter the members and data sets that contain the JCL for this product.
=====
  UserId      Member      Data set that contains the member JCL
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Configuration Location panel.
Enter	Refresh panel list.

Return to [Product List table](#).

### Configuration Location

The following panel appears for BMC CONTROL-D. Specify the data set location of the requested member of the BMC CONTROL-D Product on this system. The data set can specify the actual or an alias of the data set.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
                    BMC CONTROL-D
SRRMPROD                                     Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information

=====
Member      Data set that contains the configuration member
SECPARM     _____
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Product Install data sets.
Enter	Refresh panel list.

Return to [Product List table](#).



### Product Install Data Sets

The following panel appears for any product that requests a list of data sets for the product. Specify the actual or alias of the data set or specify the data set prefix or data set mask. If data set prefixes or data set masks are used, ensure that any data sets not associated with the product are deleted. It is recommended to use the following parameter(s) specified in the Configuration Location data set member DEFPARM:

ILPREFD

Example:

%ILPREFD%=SYS2.IOA.V6305.CTDI

Specify: (including the "." at the end of the data set qualifier and "V\*" can replace "\*")

SYS2.IOA.\*.CTDI.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
                    BMC CONTROL-D
SRRMPROD                                         Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the data sets and/or data set mask/prefix of the product installation
  data sets.
=====
  Data set names and/or Data set prefixes          Volume
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Product STC data sets.
Enter	Refresh panel list.
<a href="#">Help/PF1</a>	Display data set names and/or data set Prefixes Help.

Return to [Product List table](#).

**Product STC Data Sets**

The following panel appears for any product that requests a list of data sets for the product. Specify the actual or alias of the data set or specify the data set prefix or data set mask. The data sets, data set prefixes, or data set masks specified in this panel may require that the Products Started Task have WRITE and/or greater access. If data set prefixes or data set masks are used, ensure that any data sets not associated with the product are deleted. It is recommended to use the following parameter(s) specified in the Configuration Location data set member DEFPARM:

OLPREFD

Example:

%OLPREFD%=SYS3.IOA.V6305.CTDO

Specify: (including the "." at the end of the data set qualifier and "V\*" can replace "\*")

SYS3.IOA.\*.CTDO.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
                    BMC CONTROL-D
SRRMPROD                                     Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the data sets and/or data set mask/prefix of the product STC
  data sets.
=====
  Data set names and/or Data set prefixes          Volume
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Product User data sets.
Enter	Refresh panel list.
<a href="#">Help/PF1</a>	Display data set names and/or data set Prefixes Help.

Return to [Product List table](#).

**Product User Data Sets**

The following panel appears for any product that requests a list of data sets for the product. Specify the actual or alias of the data set or specify the data set prefix or data set mask. If data set prefixes or data set masks are used, ensure that any data sets not associated with the product are deleted. It is recommended to use the following parameter(s) specified in the Configuration Location data set member DEFPARM:

DBPREFD  
AMPREF  
AMPREFD  
JB1PREF

Example:

%DBPREFD%=SYS2.IOA.V6305.CTDR  
%AMPREF%=CTDUSR  
%AMPREFD%=CTDRSV  
%JB1PREF%=CTDJB1

Specify: (including the "." at the end of the data set qualifier and "V\*" can replace "\*")

SYS2.IOA.\*.CTDR.  
CTDUSR.  
CTDRSV.  
CTDJB1.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
                        BMC CONTROL-D
SRRMPROD                                     Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the data sets and/or data set mask/prefix of the product user
  data sets.
=====
  Data set names and/or Data set prefixes          Volume
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and return to Product List.
Enter	Refresh panel list.
<a href="#">Help/PF1</a>	Display data set names and/or data set Prefixes Help.

Return to [Product List table](#).

### BMC CONTROL-M Panels

#### STC JCL Location

The following panel appears for BMC CONTROL-M. Specify the member and data set location of each BMC CONTROL-M Product STC and/or Batch job on this system. The data set can specify the actual or an alias of the data set.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
                        BMC CONTROL-M
SRRMPROD                                     Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the Userid of the STCs or batch jobs for this product.
  Enter the members and data sets that contain the JCL for this product.
=====
  UserId      Member      Data set that contains the member JCL
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Configuration Location panel.
Enter	Refresh panel list.

Return to [Product List table](#).

### Configuration Location

The following panel appears for BMC CONTROL-M. Specify the data set location of the requested member of the BMC CONTROL-M Product on this system. The data set can specify the actual or an alias of the data set.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
                    BMC CONTROL-M
SRRMPROD                                     Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information

=====
Member      Data set that contains the configuration member
SECPARM     _____
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Product Install data sets.
Enter	Refresh panel list.

Return to [Product List table](#).

**Product Install Data Sets**

The following panel appears for any product that requests a list of data sets for the product. Specify the actual or alias of the data set or specify the data set prefix or data set mask. If data set prefixes or data set masks are used, ensure that any data sets not associated with the product are deleted. It is recommended to use the following parameter(s) specified in the Configuration Location data set member DEFPARM:

ILPREFM

Example:

%ILPREFM%=SYS3.IOA.V6305.CTMI

Specify: (including the "." at the end of the data set qualifier and "V\*" can replace "\*")

SYS3.IOA.\*.CTMI.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
                          BMC CONTROL-M
SRRMPROD                                     Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
              EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the data sets and/or data set mask/prefix of the product installation
  data sets.
=====
  Data set names and/or Data set prefixes          Volume
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Product STC data sets.
Enter	Refresh panel list.
<a href="#">Help/PF1</a>	Display data set names and/or data set Prefixes Help.

Return to [Product List table](#).

**Product STC Data Sets**

The following panel appears for any product that requests a list of data sets for the product. Specify the actual or alias of the data set or specify the data set prefix or data set mask. The data sets, data set prefixes, or data set masks specified in this panel may require that the Products Started Task have WRITE and/or greater access. If data set prefixes or data set masks are used, ensure that any data sets not associated with the product are deleted. It is recommended to use the following parameter(s) specified in the Configuration Location data set member DEFPARM:

OLPREFM

Example:

%OLPREFM%=SYS3.IOA.V6305.CTMO

Specify: (including the "." at the end of the data set qualifier and "V\*" can replace "\*")

SYS3.IOA.\*.CTMO.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
                        BMC CONTROL-M
SRRMPROD                                     Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the data sets and/or data set mask/prefix of the product STC
  data sets.
=====
  Data set names and/or Data set prefixes          Volume
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Product User data sets.
Enter	Refresh panel list.
<a href="#">Help/PF1</a>	Display data set names and/or data set Prefixes Help.

Return to [Product List table](#).

### Product User Data Sets

The following panel appears for any product that requests a list of data sets for the product. Specify the actual or alias of the data set or specify the data set prefix or data set mask. If data set prefixes or data set masks are used, ensure that any data sets not associated with the product are deleted. It is recommended to use the following parameter(s) specified in the Configuration Location data set member DEFPARM:

DBPREFM

Example:

%DBPREFM%=SYS3.IOA.V6305.CTMC

Specify: (including the "." at the end of the data set qualifier and "V\*" can replace "\*")

SYS3.IOA.\*.CTMC.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
                          BMC CONTROL-M
SRRMPROD                                     Version: v.rr
Command ==>                               Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the data sets and/or data set mask/prefix of the product user
  data sets.
=====
  Data set names and/or Data set prefixes          Volume
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to User/Application JCL data sets.
Enter	Refresh panel list.
<a href="#">Help/PF1</a>	Display data set names and/or data set Prefixes Help.

Return to [Product List table](#).



### User/Application JCL Data Sets

The following panel appears for any product that requests a list of data sets for the product. Specify the actual or alias of the data set or specify the data set prefix or data set mask. If data set prefixes or data set masks are used, ensure that any data sets not associated with the product are deleted.

```

----- Security Readiness Review Self-Audit ---- Row 1 to 1 of 1
                    BMC CONTROL-M
SRRMPROD                                     Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the data sets and/or data set mask/prefix of the user/application
  JCL data sets.
=====
  Data set names and/or Data set prefixes          Volume
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and return to Product List.
Enter	Refresh panel list.
<a href="#">Help/PF1</a>	Display data set names and/or data set Prefixes Help.

Return to [Product List table](#).

### BMC CONTROL-O Panels

#### STC JCL Location

The following panel appears for BMC CONTROL-O. Specify the member and data set location of each BMC CONTROL-O Product STC and/or Batch job on this system. The data set can specify the actual or an alias of the data set.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
                    BMC CONTROL-O
SRRMPROD                                           Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the Userid of the STCs or batch jobs for this product.
  Enter the members and data sets that contain the JCL for this product.
=====
  UserId   Member   Data set that contains the member JCL
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Configuration Location panel.
Enter	Refresh panel list.

Return to [Product List table](#).

### Configuration Location

The following panel appears for BMC CONTROL-O. Specify the data set location of the requested member of the BMC CONTROL-M Product on this system. The data set can specify the actual or an alias of the data set.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
                    BMC CONTROL-O
SRRMPROD                                     Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information

=====
Member      Data set that contains the configuration member
CTOPARM     _____
SECPARM     _____
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Product Install data sets.
Enter	Refresh panel list.

Return to [Product List table](#).

**Product Install Data Sets**

The following panel appears for any product that requests a list of data sets for the product. Specify the actual or alias of the data set or specify the data set prefix or data set mask. If data set prefixes or data set masks are used, ensure that any data sets not associated with the product are deleted. It is recommended to use the following parameter(s) specified in the Configuration Location data set member DEFPARM:

ILPREFO

Example:

%ILPREFO%=SYS3.IOA.V6305.CTOI

Specify: (including the "." at the end of the data set qualifier and "V\*" can replace "\*")

SYS3.IOA.\*.CTOI.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
                    BMC CONTROL-O
SRRMPROD                                         Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the data sets and/or data set mask/prefix of the product installation
  data sets.
=====
  Data set names and/or Data set prefixes          Volume
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Product STC data sets.
Enter	Refresh panel list.
<a href="#">Help/PF1</a>	Display data set names and/or data set Prefixes Help.

Return to [Product List table](#).

**Product STC Data Sets**

The following panel appears for any product that requests a list of data sets for the product. Specify the actual or alias of the data set or specify the data set prefix or data set mask. The data sets, data set prefixes, or data set masks specified in this panel may require that the Products Started Task have WRITE and/or greater access. If data set prefixes or data set masks are used, ensure that any data sets not associated with the product are deleted. It is recommended to use the following parameter(s) specified in the Configuration Location data set member DEFPARM:

OLPREFO

Example:

%OLPREFO%=SYS3.IOA.V6305.CTOO

Specify: (including the "." at the end of the data set qualifier and "V\*" can replace "\*")

SYS3.IOA.\*.CTOO.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
                    BMC CONTROL-O
SRRMPROD                                     Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the data sets and/or data set mask/prefix of the product STC
  data sets.
=====
  Data set names and/or Data set prefixes          Volume
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and return to Product List.
Enter	Refresh panel list.
<a href="#">Help/PF1</a>	Display data set names and/or data set Prefixes Help.

Return to [Product List table](#).

### BMC CONTROL-M/Restart Panels

#### STC JCL Location

The following panel appears for BMC CONTROL-M/Restart. Specify the member and data set location of each BMC CONTROL-M/Restart Product STC and/or Batch job on this system. The data set can specify the actual or an alias of the data set.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
                    BMC CONTROL-M/Restart
SRRMPROD
Command ==> _____ Version: v.rr
Commands:  CANCEL - Exit without saving information          Scroll ==> CSR
           EXIT/END/PF3 - Ends and saves information
Line command:  D - Delete entry
Enter the Userid of the STCs or batch jobs for this product.
Enter the members and data sets that contain the JCL for this product.
=====
  UserId   Member   Data set that contains the member JCL
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Product Install data sets.
Enter	Refresh panel list.

Return to [Product List table](#).

**Product Install Data Sets**

The following panel appears for any product that requests a list of data sets for the product. Specify the actual or alias of the data set or specify the data set prefix or data set mask. If data set prefixes or data set masks are used, ensure that any data sets not associated with the product are deleted. It is recommended to use the following parameter(s) specified in the Configuration Location data set member DEFPARM:

OLPREFR

Example:

%OLPREFR%=SYS3.IOA.V6305.CTRO

Specify: (including the "." at the end of the data set qualifier and "V\*" can replace "\*")

SYS3.IOA.\*.CTRO.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
                    BMC CONTROL-M/Restart
SRRMPROD                                         Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the data sets and/or data set mask/prefix of the product installation
  data sets.
=====
  Data set names and/or Data set prefixes          Volume
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Product User data sets.
Enter	Refresh panel list.
<a href="#">Help/PF1</a>	Display data set names and/or data set Prefixes Help.

Return to [Product List table](#).

### Product User Data Sets

The following panel appears for any product that requests a list of data sets for the product. Specify the actual or alias of the data set or specify the data set prefix or data set mask. If data set prefixes or data set masks are used, ensure that any data sets not associated with the product are deleted. It is recommended to use the following parameter(s) specified in the Configuration Location data set member CTRPARM:

AMPREFR

Example:

AMPREFR=CTRSYS

Specify: (including the "." at the end of the data set qualifier)

CTRSYS.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
                    BMC CONTROL-M/Restart
SRRMPROD                                     Version: v.rr
Command ==>                                     Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the data sets and/or data set mask/prefix of the product user
  data sets.
=====
  Data set names and/or Data set prefixes          Volume
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and return to Product List.
Enter	Refresh panel list.
<a href="#">Help/PF1</a>	Display data set names and/or data set Prefixes Help.

Return to [Product List table](#).



### BMC INCONTROL (IOA) Panels

#### STC JCL Location

The following panel appears for BMC INCONTROL (IOA). Specify the member and data set location of each BMC INCONTROL (IOA) Product STC and/or Batch job on this system. The data set can specify the actual or an alias of the data set.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
                    BMC INCONTROL (IOA)
SRRMPROD                                     Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the Userid of the STCs or batch jobs for this product.
  Enter the members and data sets that contain the JCL for this product.
=====
  UserId      Member      Data set that contains the member JCL
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Configuration Location panel.
Enter	Refresh panel list.

Return to [Product List table](#).

### Configuration Location

The following panel appears for BMC INCONTROL (IOA). Specify the data set location of the requested member of the BMC INCONTROL (IOA) Product on this system. The data set can specify the actual or an alias of the data set.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
                    BMC INCONTROL (IOA)
SRRMPROD                                     Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information

=====
Member      Data set that contains the configuration member
SECPARM     _____
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Product Install data sets.
Enter	Refresh panel list.

Return to [Product List table](#).

**Product Install Data Sets**

The following panel appears for any product that requests a list of data sets for the product. Specify the actual or alias of the data set or specify the data set prefix or data set mask. If data set prefixes or data set masks are used, ensure that any data sets not associated with the product are deleted. It is recommended to use the following parameter(s) specified in the Configuration Location data set member DEFPARM:

BASEPREF	ILPREFA	SPAPREF	SPCPREF	SPCPREFD
SPCPREFT	SPDPREF	STEPLIB	STEPLIBE	

Example:

%BASEPREF%=SYS2.IOA.V6305.IOADB	%ILPREFA%=SYS2.IOA.V6305.IOAI
%SPAPREF%=SYS2.IOA.V6305.IOASMPA	%SPCPREF%=SYS2.IOA.V6305.IOASMPC
%SPCPREFD%=SYS2.IOA.V6305.IOASMPC	%SPCPREFT%=SYS2.IOA.V6305.IOASMPC
%SPDPREF%=SYS2.IOA.V6305.IOASMPD	%STEPLIB%=SYS2.IOA.V6305.LOADLIB
%STEPLIBE%=SYS2.IOA.V6305.LOADE	

Specify: (including the "." at the end of the data set qualifier and "V\*" can replace "\*")

SYS2.IOA.*.IOADB.	SYS2.IOA.*.IOAI.
SYS2.IOA.*.IOASMPA.	SYS2.IOA.*.IOASMPC.
SYS2.IOA.*.IOASMPD.	SYS2.IOA.*.LOAD

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
              BMC INCONTROL (IOA)
SRRMPROD
Command ==> _____ Version: v.rr
Commands:  CANCEL - Exit without saving information
           EXIT/END/PF3 - Ends and saves information
Line command:  D - Delete entry
Enter the data sets and/or data set mask/prefix of the product installation
data sets.
=====
Data set names and/or Data set prefixes          Volume
-----
***** Bottom of data *****
    
```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Product STC data sets.
Enter	Refresh panel list.
<a href="#">Help/PF1</a>	Display data set names and/or data set Prefixes Help.

Return to [Product List table](#).

### Product STC Data Sets

The following panel appears for any product that requests a list of data sets for the product. Specify the actual or alias of the data set or specify the data set prefix or data set mask. The data sets, data set prefixes, or data set masks specified in this panel may require that the Products Started Task have WRITE and/or greater access. If data set prefixes or data set masks are used, ensure that any data sets not associated with the product are deleted. It is recommended to use the following parameter(s) specified in the Configuration Location data set member DEFPARM:

OLPREFA

Example:

%OLPREFA%=SYS3.IOA.V6305.IOAO

Specify: (including the "." at the end of the data set qualifier and "V\*" can replace "\*")

SYS3.IOA.\*.IOAO.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
                    BMC INCONTROL (IOA)
SRRMPROD                                     Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the data sets and/or data set mask/prefix of the product STC
  data sets.
=====
  Data set names and/or Data set prefixes          Volume
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Product User data sets.
Enter	Refresh panel list.
<a href="#">Help/PF1</a>	Display data set names and/or data set Prefixes Help.

Return to [Product List table](#).

### Product User Data Sets

The following panel appears for any product that requests a list of data sets for the product. Specify the actual or alias of the data set or specify the data set prefix or data set mask. If data set prefixes or data set masks are used, ensure that any data sets not associated with the product are deleted. It is recommended to use the following parameter(s) specified in the Configuration Location data set member DEFPARM:

DBPREFA

Example:

%DBPREFA%=SYS3.IOA.V6305.IOAC

Specify: (including the "." at the end of the data set qualifier and "V\*" can replace "\*\*")

SYS3.IOA.\*.IOAC.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
                    BMC INCONTROL (IOA)
SRRMPROD                                     Version: v.rr
Command ==>                                     Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the data sets and/or data set mask/prefix of the product user
  data sets.
=====
  Data set names and/or Data set prefixes          Volume
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and return to Product List.
Enter	Refresh panel list.
<a href="#">Help/PF1</a>	Display data set names and/or data set Prefixes Help.

Return to [Product List table](#).

### BMC MAINVIEW for z/OS Panels

#### Subsystem Identifier

The following panel appears for any product that requires a list of subsystem identifiers be specified for the product. Use the value specified for the SSID variable specified in the MV\$CAS (CAS) and MV\$MVS (PAS) proclib members.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
                    BMC MAINVIEW for z/OS
SRRMPROD                                                    Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the SubSystem Identifier for all occurrences of this product.

=====
  SSID
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to STC JCL Location.
Enter	Refresh panel list.

Return to [Product List table](#).

**STC JCL Location**

The following panel appears for BMC MAINVIEW for z/OS. Specify the member and data set location of each BMC MAINVIEW for z/OS Product STC and/or Batch job on this system. The data set can specify the actual or an alias of the data set.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
                    BMC MAINVIEW for z/OS
SRRMPROD                                     Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the Userid of the STCs or batch jobs for this product.
  Enter the members and data sets that contain the JCL for this product.
=====
  UserId      Member      Data set that contains the member JCL
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Resource Identification panel.
Enter	Refresh panel list.

Return to [Product List table](#).

**Resource Identification**

One of the following panels will be displayed depending on the ACP running on the system. The following are links to each ACP panel for BMC MAINVIEW for z/OS.

- [ACF2](#)
- [RACF](#)
- [TSS](#)

**ACF2**

Enter the Resource Type used by the BMC MAINVIEW for z/OS product.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
                    BMC MAINVIEW for z/OS
SRRMPROD                                     Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information

Enter the Resource Type for the product.

=====
Member   Resource Type
MAINVIEW _____
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Configuration Location panel.
Enter	Refresh panel list.

Return to [Product List table](#).



**RACF**

Enter the Resource Class used by the BMC MAINVIEW for z/OS product.

```

----- Security Readiness Review Self-Audit ---- Row 1 to 1 of 1
              BMC MAINVIEW for z/OS

SRRMPROD
Command ==> _____ Version: v.rr
                Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information

  Enter the Resource Class for the product.

=====
Member   Resource Class
MAINVIEW _____
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Configuration Location panel.
Enter	Refresh panel list.

Return to [Product List table](#).

**TSS**

Enter the Resource Class used by the BMC MAINVIEW for z/OS product.

```
----- Security Readiness Review Self-Audit ---- Row 1 to 1 of 1
                BMC MAINVIEW for z/OS

SRRMPROD
Command ==> _____ Version: v.rr
Commands:  CANCEL - Exit without saving information      Scroll ==> CSR
           EXIT/END/PF3 - Ends and saves information

Enter the Resource Class for the product.

=====
Member   Resource Class
MAINVIEW _____
***** Bottom of data *****
```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Saves information and continues to Configuration Location panel.
Enter	Refresh panel list.

Return to [Product List table](#).

### Configuration Location

The following panel appears for BMC MAINVIEW for z/OS. Specify the member and data set locations of each BMC MAINVIEW for z/OS Product on this system. The data set can specify the actual or an alias of the data set.

```

----- Security Readiness Review Self-Audit ---- Row 1 to 2 of 2
                    BMC MAINVIEW for z/OS
SRRMPROD                                     Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
              EXIT/END/PF3 - Ends and saves information
  Enter member and data set name that contains the product configuration.

=====
STC/JOB  Member   Data set that contains the configuration member
BBMTSSxx _____
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Product Install data sets.
Enter	Refresh panel list.

Return to [Product List table](#).

### Product Install Data Sets

The following panel appears for any product that requests a list of data sets for the product. Specify the actual or alias of the data set or specify the data set prefix or data set mask. If data set prefixes or data set masks are used, ensure that any data sets not associated with the product are deleted.

```

----- Security Readiness Review Self-Audit ---- Row 1 to 1 of 1
                    BMC MAINVIEW for z/OS
SRRMPROD                                     Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the data sets and/or data set mask/prefix of the product installation
  data sets.
=====
  Data set names and/or Data set prefixes          Volume
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Product STC data sets.
Enter	Refresh panel list.
<a href="#">Help/PF1</a>	Display data set names and/or data set Prefixes Help.

Return to [Product List table](#).

### Product STC Data Sets

The following panel appears for any product that requests a list of data sets for the product. Specify the actual or alias of the data set or specify the data set prefix or data set mask. The data sets, data set prefixes, or data set masks specified in this panel may require that the Products Started Task have WRITE and/or greater access. If data set prefixes or data set masks are used, ensure that any data sets not associated with the product are deleted.

```

----- Security Readiness Review Self-Audit ---- Row 1 to 1 of 1
                    BMC MAINVIEW for z/OS
SRRMPROD                                     Version: v.rr
Command ==>>> _____ Scroll ==>>> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the data sets and/or data set mask/prefix of the product STC
  data sets.
=====
  Data set names and/or Data set prefixes          Volume
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and return to Product List.
Enter	Refresh panel list.
<a href="#">Help/PF1</a>	Display data set names and/or data set Prefixes Help.

Return to [Product List table](#).

### CA AUDITOR (CA EXAMINE)

#### Product Install Data Sets

The following panel appears for any product that requests a list of data sets for the product. Specify the actual or alias of the data set or specify the data set prefix or data set mask. If data set prefixes or data set masks are used, ensure that any data sets not associated with the product are deleted.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
                          CA AUDITOR (CA EXAMINE)
SRRMPROD                                     Version: v.rr
Command ==>>> _____ Scroll ==>>> CSR
  Commands:  CANCEL - Exit without saving information
              EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the data sets and/or data set mask/prefix of the product installation
  data sets.
=====
  Data set names and/or Data set prefixes          Volume
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Product User data sets.
Enter	Refresh panel list.
<a href="#">Help/PF1</a>	Display data set names and/or data set Prefixes Help.

Return to [Product List table](#).

**Product User Data Sets**

The following panel appears for any product that requests a list of data sets for the product. Specify the actual or alias of the data set or specify the data set prefix or data set mask. If data set prefixes or data set masks are used, ensure that any data sets not associated with the product are deleted. One of the data sets is the CAIDBS1 data set. Other data sets in this category are user data sets that contain report results for executing the CA Auditor batch jobs.

```
----- Security Readiness Review Self-Audit ---- Row 1 to 1 of 1
              CA AUDITOR (CA EXAMINE)
SRRMPROD                                         Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the data sets and/or data set mask/prefix of the product user
  data sets.
=====
  Data set names and/or Data set prefixes          Volume
-----
***** Bottom of data *****
```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and return to Product List.
Enter	Refresh panel list.
<a href="#">Help/PF1</a>	Display data set names and/or Data set Prefixes Help.

Return to [Product List table](#).

## CA MICS Resource Management

### Product Install Data Sets

The following panel appears for any product that requests a list of data sets for the product. Specify the actual or alias of the data set or specify the data set prefix or data set mask. If data set prefixes or data set masks are used, ensure that any data sets not associated with the product are deleted.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
              CA MICS Resource Management
SRRMPROD                                           Version: v.rr
Command ==>>>                                     Scroll ==>>> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the data sets and/or data set mask/prefix of the product installation
  data sets.
=====
  Data set names and/or Data set prefixes          Volume
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and return to Product List.
Enter	Refresh panel list.
<a href="#">Help/PF1</a>	Display data set names and/or Data set Prefixes Help.

Return to [Product List table](#).



### Product User Data Sets

The following panel appears for any product that requests a list of data sets for the product. Specify the actual or alias of the data set or specify the data set prefix or data set mask. If data set prefixes or data set masks are used, ensure that any data sets not associated with the product are deleted.

```

----- Security Readiness Review Self-Audit ---- Row 1 to 1 of 1
              CA MICS Resource Management
SRRMPROD                                         Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
              EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the data sets and/or data set mask/prefix of the product user
  data sets.
=====
  Data set names and/or Data set prefixes          Volume
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and return to Product List.
Enter	Refresh panel list.
<a href="#">Help/PF1</a>	Display data set names and/or data set Prefixes Help.

Return to [Product List table](#).

### CA MIM Panels

#### STC JCL Location

The following panel appears for CA MIM. Specify the member and data set location of each CA MIM Product STC and/or Batch job on this system. The data set can specify the actual or an alias of the data set.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
              CA MIM Resource Sharing for z/OS
SRRMPROD
Command ==> _____ Version: v.rr
Commands:  CANCEL - Exit without saving information      Scroll ==> CSR
           EXIT/END/PF3 - Ends and saves information
Line command:  D - Delete entry
Enter the Userid of the STCs or batch jobs for this product.
Enter the members and data sets that contain the JCL for this product.
=====
  UserId   Member   Data set that contains the member JCL
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Product Install data sets.
Enter	Refresh panel list.

Return to [Product List table](#).

### Product Install Data Sets

The following panel appears for any product that requests a list of data sets for the product. Specify the actual or alias of the data set or specify the data set prefix or data set mask. If data set prefixes or data set masks are used, ensure that any data sets not associated with the product are deleted.

```

----- Security Readiness Review Self-Audit ---- Row 1 to 1 of 1
              CA MIM Resource Sharing for z/OS
SRRMPROD                                         Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
              EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the data sets and/or data set mask/prefix of the product installation
  data sets.
=====
  Data set names and/or Data set prefixes          Volume
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Product STC data sets.
Enter	Refresh panel list.
<a href="#">Help/PF1</a>	Display data set names and/or data set Prefixes Help.

Return to [Product List table](#).

### Product STC Data Sets

The following panel appears for any product that requests a list of data sets for the product. Specify the actual or alias of the data set or specify the data set prefix or data set mask. The data sets, data set prefixes, or data set masks specified in this panel may require that the Products Started Task have WRITE and/or greater access. If data set prefixes or data set masks are used, ensure that any data sets not associated with the product are deleted.

```

----- Security Readiness Review Self-Audit ---- Row 1 to 1 of 1
              CA MIM Resource Sharing for z/OS
SRRMPROD
Command ==> _____ Version: v.rr
Commands:  CANCEL - Exit without saving information
           EXIT/END/PF3 - Ends and saves information
Line command:  D - Delete entry
Enter the data sets and/or data set mask/prefix of the product STC
data sets.
=====
Data set names and/or Data set prefixes          Volume
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and return to Product List.
Enter	Refresh panel list.
<a href="#">Help/PF1</a>	Display data set names and/or data set Prefixes Help.

Return to [Product List table](#).

### Catalog Solution Panels

#### Product Loadlib Dataset

The following panel appears for any product that requests a list of data sets for the product. Specify the actual or alias of the data set or specify the data set prefix or data set mask. If data set prefixes or data set masks are used, ensure that any data sets not associated with the product are deleted.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
                        Catalog Solutions
SRRMPROD                                     Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information

Enter the loadlib data set for the product.

=====
Loadlib data set name
_____
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Product Install data sets.
Enter	Refresh panel list.

Return to [Product List table](#).

### Product Install Data Sets

The following panel appears for any product that requests a list of data sets for the product. Specify the actual or alias of the data set or specify the data set prefix or data set mask. If data set prefixes or data set masks are used, ensure that any data sets not associated with the product are deleted.

```

----- Security Readiness Review Self-Audit ---- Row 1 to 1 of 1
                Catalog Solutions
SRRMPROD                                           Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the data sets and/or data set mask/prefix of the product installation
  data sets.
=====
  Data set names and/or Data set prefixes          Volume
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and return to Product List.
Enter	Refresh panel list.
<a href="#">Help/PF1</a>	Display data set names and/or data set Prefixes Help.

Return to [Product List table](#).

### CA1 Panels

#### STC JCL Location

The following panel appears for CL/SuperSession. Specify the member and data set location of CL/SuperSession STC on this system. The data set can specify the actual or an alias of the data set.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
                    CA1 Tape Management System
SRRMPROD                                     Version: v.rr
Command ===> _____ Scroll ===> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information

  Enter the Userid of the STC or batch job for this product.
  Enter the member and data set that contains the JCL for this product.
=====
UserId      Member      Data set that contains the member JCL
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Module Location panel.
Enter	Refresh panel list.

Return to [Product List table](#).

**Module Location**

The following panel appears for CA1. Specify the data set location of the listed members. The data set can specify the actual or an alias of the data set.

```

----- Security Readiness Review Self-Audit ---- Row 1 to 2 of 2
              CA1 Tape Management System
SRRMPROD                                         Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information

  Enter the data set that contains the listed programs.

=====
Program  Program Data set location
TMSSECAB _____
TMSTMVT  _____
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Configuration Location.
Enter	Refresh panel list.

Return to [Product List table](#).



### Configuration Location

The following panel appears for CA1. Specify the member and data set location for CA1 configuration on this system. The data set can specify the actual or an alias of the data set.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
              CA1 Tape Management System
SRRMPROD                                         Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
  Enter member and data set name that contains the product configuration.

=====
Prefix  Member  Data set that contains the configuration member
TMOYSxxx _____
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Product Install data sets.
Enter	Refresh panel list.

Return to [Product List table](#).

### Product Install Data Sets

The following panel appears for any product that requests a list of data sets for the product. Specify the actual or alias of the data set or specify the data set prefix or data set mask. If data set prefixes or data set masks are used, ensure that any data sets not associated with the product are deleted.

```

----- Security Readiness Review Self-Audit ---- Row 1 to 1 of 1
              CA1 Tape Management System
SRRMPROD                                     Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
              EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the data sets and/or data set mask/prefix of the product installation
  data sets.
=====
  Data set names and/or Data set prefixes          Volume
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to other data sets.
Enter	Refresh panel list.
<a href="#">Help/PF1</a>	Display data set names and/or data set Prefixes Help.

Return to [Product List table](#).

**Product STC Data Sets**

The following panel appears for any product that requests a list of data sets for the product. Specify the actual or alias of the data set or specify the data set prefix or data set mask. If data set prefixes or data set masks are used, ensure that any data sets not associated with the product are deleted. The data sets, data set prefixes, or data set masks specified in this panel may require that the Products Started Task has WRITE and/or greater access.

```

----- Security Readiness Review Self-Audit ---- Row 1 to 1 of 1
              CA1 Tape Management System
SRRMPROD                                     Version: v.rr
Command ==>>> _____ Scroll ==>>> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the data sets and/or data set mask/prefix of the product STC
  data sets.
=====
  Data set names and/or Data set prefixes          Volume
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to other data sets.
Enter	Refresh panel list.
<a href="#">Help/PF1</a>	Display data set names and/or data set Prefixes Help.

Return to [Product List table](#).

**Other Data Sets**

The following panel appears for additional data sets for the product. Specify the actual or alias of the data set or specify the data set prefix or data set mask. If data set prefixes or data set masks are used, ensure that any data sets not associated with the product are deleted.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
                  CA1 Tape Management System
SRRMPROD                                     Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
              EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the data sets and/or data set mask/prefix of the TMC, AUDIT, and
  optional RDS and VPD data sets.
=====
  Data set names and/or Data set prefixes          Volume
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and return to Product List.
Enter	Refresh panel list.
<a href="#">Help/PF1</a>	Display data set names and/or data set Prefixes Help.

Return to [Product List table](#).

### CA Common Services (CCS) Panels

#### STC JCL Location

The following panel appears for CA Common Services (CCS). Specify the member and data set location of CCS STC on this system. The data set can specify the actual or an alias of the data set.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
                          CA Common Services (CCS)
SRRMPROD                                     Version: v.rr
Command ===> _____ Scroll ===> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information

  Enter the Userid of the STC or batch job for this product.
  Enter the member and data set that contains the JCL for this product.
=====
UserId      Member      Data set that contains the member JCL
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Product Install data sets.
Enter	Refresh panel list.

Return to [Product List table](#).

### Product Install Data Sets

The following panel appears for any product that requests a list of data sets for the product. Specify the actual or alias of the data set or specify the data set prefix or data set mask. If data set prefixes or data set masks are used, ensure that any data sets not associated with the product are deleted. These data sets will be reviewed with the other Comm Server data sets (TCPRPT).

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
                    CA Common Services (CCS)
SRRMPROD                                           Version: v.rr
Command ==>>> _____ Scroll ==>>> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the data sets and/or data set mask/prefix of the product installation
  data sets.
=====
  Data set names and/or Data set prefixes          Volume
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and return to Product List.
Enter	Refresh panel list.
<a href="#">Help/PF1</a>	Display data set names and/or data set Prefixes Help.

Return to [Product List table](#).

### CICS Panels

#### STC JCL Location

The following panel appears for CICS. Specify the member and data set location of each CICS region on this system. Additional CICS STCs can be entered on the blank entry line or by overtyping the new CICS STCs on any or all filled lines. The data set can specify the actual or an alias of the data set.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
                CICS Transaction Server
SRRMPROD                                           Version: v.rr
Command ==>> _____ Scroll ==>> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the Userid of the STCs or batch jobs for this product.
  Enter the members and data sets that contain the JCL for this product.
  P/T values - P or space = Production   T = Test/Development
=====
  UserId  P/T Member   Data set that contains the member JCL
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Module Location panel.
Enter	Refresh panel list.

Return to [Product List table](#).

**Module Location**

The following panel appears listing all of the CICS STCs specified in the previous panel. Specify the member and data set location of the DFHSITxx member for each CICS STC, which is identified in the Member column. If only one DFHSITxx member is used by all CICS STCs, only one entry may be filled in for this panel. The data set that contains the DFHSITxx member can specify the actual or an alias of the data set.

```

----- Security Readiness Review Self-Audit ---- Row 1 to 1 of 1
              CICS Transaction Server
SRRMPROD                                         Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information

Enter the DFHSIT program and data set for each CICS region.

=====
Member   Program  Data set that contains the program
xxxxxxx _____
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Resource Identification panel.
Enter	Refresh panel list.

Return to [Product List table](#).



**Resource Identification**

One of the following panels will be displayed depending on the ACP running on the system. The following are links to each ACP panel for CICS.

- [ACF2](#)
- [RACF](#)
- [TSS](#)

**ACF2**

Enter the Resource Type, MUSASS, and MLID for each CICS STC. If only one set of these entries is being used by multiple CICS STCs, specify only one. Repeating the entries for each CICS STC is not necessary.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
                    CICS Transaction Server
SRRMPROD
Command ===> _____ Version: v.rr
                    Scroll ===> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information

  Enter the Resource Type and the MUSASS and MLID pair for each region.

=====
Member  Resource Type  MUSASS  MLID
xxxxxxx
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Product Install data sets panel.
Enter	Refresh panel list.

Return to [Product List table](#).

**RACF**

Enter the Resource Classes for the member and group resource classes. If only one set of these entries is being used by multiple CICS STCs, specify only one. Repeating the entries for each CICS STC is not necessary.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
                  CICS Transaction Server
SRRMPROD                                         Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
  Enter the Resource Class and the Resource Class Group.
    example: (TCICSTRN and + GCICSTRN)

=====
Member   Resource Classes (include Group Resource class)
xxxxxxx _____
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Product Install data sets panel.
Enter	Refresh panel list.

Return to [Product List table](#).

**TSS**

Enter the Resource Class for each CICS STC. If only one set of these entries is being used by multiple CICS STCs, specify only one. Repeating the entries for each CICS STC is not necessary.

```

----- Security Readiness Review Self-Audit ---- Row 1 to 1 of 1
              CICS Transaction Server
SRRMPROD                                         Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information

Enter the Resource Class.

=====
Member      Resource Classes
xxxxxxxxx _____
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Product Install data sets panel.
Enter	Refresh panel list.

Return to [Product List table](#).

### Product Install Data Sets

The following panel appears for any product that requests a list of data sets for the product. Specify the actual or alias of the data set or specify the data set prefix or data set mask. If data set prefixes or data set masks are used, ensure that any data sets not associated with the product are deleted.

```

----- Security Readiness Review Self-Audit ---- Row 1 to 1 of 1
              CICS Transaction Server
SRRMPROD                                         Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
              EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the data sets and/or data set mask/prefix of the product installation
  data sets.
=====
  Data set names and/or Data set prefixes          Volume
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Product STC data sets.
Enter	Refresh panel list.
<a href="#">Help/PF1</a>	Display data set names and/or data set Prefixes Help.

Return to [Product List table](#).

### Product STC Data Sets

The following panel appears for any product that requests a list of data sets for the product. Specify the actual or alias of the data set or specify the data set prefix or data set mask. The data sets, data set prefixes, or data set masks specified in this panel may require that the Products Started Task have WRITE and/or greater access. If data set prefixes or data set masks are used, ensure that any data sets not associated with the product are deleted.

```

----- Security Readiness Review Self-Audit ---- Row 1 to 1 of 1
                    CICS Transaction Server
SRRMPROD                                     Version: v.rr
Command ==>>> _____ Scroll ==>>> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the data sets and/or data set mask/prefix of the product STC
  data sets.
=====
  Data set names and/or Data set prefixes          Volume
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and return to Product List.
Enter	Refresh panel list.
<a href="#">Help/PF1</a>	Display data set names and/or data set Prefixes Help.

Return to [Product List table](#).

### CL/SuperSession Panels

#### STC JCL Location

The following panel appears for CL/SuperSession. Specify the member and data set location of CL/SuperSession STC on this system. The data set can specify the actual or an alias of the data set.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
                    CL/SuperSession
SRRMPROD                                     Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information

  Enter the Userid of the STC or batch job for this product.
  Enter the member and data set that contains the JCL for this product.
=====
UserId      Member      Data set that contains the member JCL
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Configuration Setting panel.
<a href="#">Enter</a>	Save information and continue to Configuration Setting panel.

Return to [Product List table](#).

### Configuration Settings

The following panel appears for CL/SuperSession. Specify the values from each of the two Profile panels specified in the CL/SuperSession STC on this system. If necessary, use the PF7 and PF8 keys to scroll up and down on the menu to enter all requested information.

```

----- Security Readiness Review Self-Audit -----
                          CL/SuperSession
SRRMPROD                               Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
              Enter - Ends and saves information
=====

From the Administrator menu provide the following entries from:

GLOBAL Common Profile Segment:
  1. Administrator authority      : _      (Y or N)
  2. Maintain customized menu    : _      (Y or N)
  3. Add sessions to the menu    : _      (Y or N)
  4. Resource validation         : _      (A, S, or B)
  5. Timeout interval           : _____ (HH:MM)
  6. Group profile name          : N/A

SupSess GLOBAL Profile Segment:
  1. Maintain trigger profile    : _      (Y or N)
  2. Add triggers to profile     : _      (Y or N)
  3. Modify triggers in profile  : _      (Y or N)
  4. Switch terminals           : _      (Y or N)
  5. Preserve Sessions upon exit : _      (Y or N)
=====

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">Enter</a>	Save information and continue to Product Install data sets.

Return to [Product List table](#).

### Product Install Data Sets

The following panel appears for any product that requests a list of data sets for the product. Specify the actual or alias of the data set or specify the data set prefix or data set mask. If data set prefixes or data set masks are used, ensure that any data sets not associated with the product are deleted.

```

----- Security Readiness Review Self-Audit ---- Row 1 to 1 of 1
                    CL/SuperSession
SRRMPROD                                     Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the data sets and/or data set mask/prefix of the product installation
  data sets.
=====
  Data set names and/or Data set prefixes          Volume
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Product STC data sets.
Enter	Refresh panel list.
<a href="#">Help/PF1</a>	Display data set names and/or data set Prefixes Help.

Return to [Product List table](#).



### Product STC Data Sets

The following panel appears for any product that requests a list of data sets for the product. Specify the actual or alias of the data set or specify the data set prefix or data set mask. The data sets, data set prefixes, or data set masks specified in this panel may require that the Products Started Task have WRITE and/or greater access. If data set prefixes or data set masks are used, ensure that any data sets not associated with the product are deleted.

```

----- Security Readiness Review Self-Audit ---- Row 1 to 1 of 1
                          CL/SuperSession
SRRMPROD                                     Version: v.rr
Command ==>>> _____ Scroll ==>>> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the data sets and/or data set mask/prefix of the product STC
  data sets.
=====
  Data set names and/or Data set prefixes          Volume
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and return to Product List.
Enter	Refresh panel list.
<a href="#">Help/PF1</a>	Display data set names and/or data set Prefixes Help.

Return to [Product List table](#).

### IBM Comm Server File Transfer Protocol (CSFTP) Panels

#### STC JCL Location

The following panel appears for IBM Comm Server File Transfer Protocol (CSFTP). Specify the member and data set location of CSFTP STC on this system. The data set can specify the actual or an alias of the data set.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
                IBM Comm Server File Transfer Protocol (CSFTP)
SRRMPROD                                           Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information

  Enter the Userid of the STC or batch job for this product.
  Enter the member and data set that contains the JCL for this product.
=====
UserId      Member      Data set that contains the member JCL
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and return to Product List.
Enter	Refresh panel list.

Return to [Product List table](#).

### IBM Comm Server Simple Mail Transfer Protocol (CSSMTP) Panels

#### STC JCL Location

The following panel appears for IBM Comm Server Simple Mail Transfer Protocol (CSSMTP). Specify the member and data set location of CSSMTP STC on this system. The data set can specify the actual or an alias of the data set.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
          IBM Comm Server Simple Mail Transfer Protocol (CSSMTP)
SRRMPROD                                     Version: v.rr
Command ==>> _____ Scroll ==>> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information

  Enter the Userid of the STC or batch job for this product.
  Enter the member and data set that contains the JCL for this product.
=====
UserId   Member   Data set that contains the member JCL
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and return to Product List.
Enter	Refresh panel list.

Return to [Product List table](#).

### IBM Comm Server TCP/IP (CSTCP) Panels

#### STC JCL Location

The following panel appears for IBM Comm Server TCP/IP (CSTCP). Specify the member and data set location of CSTCP STC on this system. The data set can specify the actual or an alias of the data set.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
                IBM Comm Server TCP/IP (CSTCP)
SRRMPROD                                           Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information

  Enter the Userid of the STC or batch job for this product.
  Enter the member and data set that contains the JCL for this product.
=====
UserId      Member      Data set that contains the member JCL
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and return to Product List.
Enter	Refresh panel list.

Return to [Product List table](#).

### IBM Comm Server TN3270E Telnet Server (CSTNT) Panels

#### STC JCL Location

The following panel appears for IBM Comm Server TN3270E Telnet Server (CSTNT). Specify the member and data set location of CSTNT STC on this system. The data set can specify the actual or an alias of the data set.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
                IBM Comm Server TN3270E Telnet Server (CSTNT)
SRRMPROD                                           Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information

  Enter the Userid of the STC or batch job for this product.
  Enter the member and data set that contains the JCL for this product.
=====
UserId      Member      Data set that contains the member JCL
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and return to Product List.
Enter	Refresh panel list.

Return to [Product List table](#).

**FDR Panels**

**Module Location**

The following panel appears for Fast Dump Restore (FDR). Specify the data set location of the listed members. The data set can specify the actual or an alias of the data set.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
                          FDR
SRRMPROD                                     Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information

Enter the data set that contains the listed programs.

=====
Program  Program Data set location
FDROPT  _____
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Product Install data sets.
<a href="#">Enter</a>	Save information and continue to Product Install data sets.

Return to [Product List table](#).

### Product Install Data Sets

The following panel appears for any product that requests a list of data sets for the product. Specify the actual or alias of the data set or specify the data set prefix or data set mask. If data set prefixes or data set masks are used, ensure that any data sets not associated with the product are deleted.

```

----- Security Readiness Review Self-Audit ---- Row 1 to 1 of 1
                        FDR
SRRMPROD                                     Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the data sets and/or data set mask/prefix of the product installation
  data sets.
=====
  Data set names and/or Data set prefixes          Volume
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and return to Product List.
Enter	Refresh panel list.
<a href="#">Help/PF1</a>	Display data set names and/or data set Prefixes Help.

Return to [Product List table](#).

**FEP Panels**

**All Product Data Sets**

The following panel appears for any product that requests a list of data sets for the product. Specify the actual or alias of the data set or specify the data set prefix or data set mask. If data set prefixes or data set masks are used, ensure that any data sets not associated with the product are deleted.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
                          Front End Processor
SRRMPROD                                     Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
              EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the data sets and/or data set mask/prefix of all of the product
  data sets.
=====
  Data set names and/or Data set prefixes          Volume
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and return to Product List.
Enter	Refresh panel list.
<a href="#">Help/PF1</a>	Display data set names and/or data set Prefixes Help.

Return to [Product List table](#).



### IBM Hardware Configuration Definition (HCD) Panels

#### Product Install Data Sets

The following panel appears for any product that requests a list of data sets for the product. Specify the actual or alias of the data set or specify the data set prefix or data set mask. If data set prefixes or data set masks are used, ensure that any data sets not associated with the product are deleted.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
              IBM Hardware Configuration Definition (HCD)
SRRMPROD                                     Version: v.rr
Command ==>>> _____ Scroll ==>>> CSR
  Commands:  CANCEL - Exit without saving information
              EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the data sets and/or data set mask/prefix of the product installation
  data sets.
=====
  Data set names and/or Data set prefixes          Volume
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Product User data sets.
Enter	Refresh panel list.
<a href="#">Help/PF1</a>	Display data set names and/or data set Prefixes Help.

Return to [Product List table](#).

### Product User Data Sets

The following panel appears for any product that requests a list of data sets for the product. Specify the actual or alias of the data set or specify the data set prefix or data set mask. If data set prefixes or data set masks are used, ensure that any data sets not associated with the product are deleted. These data sets are the IODF data sets available to this system. The currently active IODF can be determined from the results of IPLINFO script; find the “currently active IODF data set is” statement.

```

----- Security Readiness Review Self-Audit ---- Row 1 to 1 of 1
              IBM Hardware Configuration Definition (HCD)
SRRMPROD                                     Version: v.rr
Command ==>>> _____ Scroll ==>>> CSR
  Commands:  CANCEL - Exit without saving information
              EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the data sets and/or data set mask/prefix of the product user
  data sets.
=====
  Data set names and/or Data set prefixes          Volume
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and return to Product List.
Enter	Refresh panel list.
<a href="#">Help/PF1</a>	Display data set names and/or data set Prefixes Help.

Return to [Product List table](#).

### IBM Health Checker

#### STC JCL Location

The following panel appears for IBM Health Checker. Specify the member and data set location of each IBM Health Checker Product STC and/or Batch job on this system. The data set can specify the actual or an alias of the data set.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
                    IBM Health Checker
SRRMPROD                                           Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the Userid of the STCs or batch jobs for this product.
  Enter the members and data sets that contain the JCL for this product.
=====
  UserId    Member    Data set that contains the member JCL
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Product Install data sets.
Enter	Refresh panel list.

Return to [Product List table](#).

### Product STC Data Sets

The following panel appears for any product that requests a list of data sets for the product. Specify the actual or alias of the data set or specify the data set prefix or data set mask. The data sets, data set prefixes, or data set masks specified in this panel may require that the Products Started Task have WRITE and/or greater access. If data set prefixes or data set masks are used, ensure that any data sets not associated with the product are deleted. The data set that should be specified is identified in the STC member under the DD statement of HZSPDATA.

```

----- Security Readiness Review Self-Audit ---- Row 1 to 1 of 1
                    IBM Health Checker
SRRMPROD                                         Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
Line command: D - Delete entry
Enter the data sets and/or data set mask/prefix of the product STC
data sets.
=====
Data set names and/or Data set prefixes          Volume
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and return to Product List.
Enter	Refresh panel list.
<a href="#">Help/PF1</a>	Display data set names and/or data set Prefixes Help.

Return to [Product List table](#).

### IBM Integrated Crypto Service Facility (ICSF) Panels

#### STC JCL Location

The following panel appears for ICSF. Specify the member and data set locations of the ICSF STC on this system. The data set can specify the actual or an alias of the data set.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
              IBM Integrated Crypto Service Facility (ICSF)
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
              EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the Userid of the STCs or batch jobs for this product.
  Enter the members and data sets that contain the JCL for this product.
=====
UserId      Member      Data set that contains the member JCL
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Configuration Location panel.
<a href="#">Enter</a>	Save information and continue to Configuration Location panel.

Return to [Product List table](#).

### Configuration Location

The following panel appears for ICSF. Specify the member and data set location for ICSF configuration on this system. The data set can specify the actual or an alias of the data set.

```

----- Security Readiness Review Self-Audit ---- Row 1 to 2 of 2
              IBM Integrated Crypto Service Facility (ICSF)
SRRMPROD                                         Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
              EXIT/END/PF3 - Ends and saves information
  Enter member and data set name that contains the product configuration.

=====
Prefix  Member  Data set that contains the configuration member
CSFPRMxx _____
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Product Install data sets.
<a href="#">Enter</a>	Save information and continue to Product Install data sets.

Return to [Product List table](#).

### Product Install Data Sets

The following panel appears for any product that requests a list of data sets for the product. Specify the actual or alias of the data set or specify the data set prefix or data set mask. If data set prefixes or data set masks are used, ensure that any data sets not associated with the product are deleted.

```

----- Security Readiness Review Self-Audit ---- Row 1 to 1 of 1
              IBM Integrated Crypto Service Facility (ICSF)
SRRMPROD                                         Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
              EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the data sets and/or data set mask/prefix of the product installation
  data sets.
=====
  Data set names and/or Data set prefixes          Volume
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Product STC data sets.
Enter	Refresh panel list.
<a href="#">Help/PF1</a>	Display data set names and/or data set Prefixes Help.

Return to [Product List table](#).

### Product STC Data Sets

The following panel appears for any product that requests a list of data sets for the product. Specify the actual or alias of the data set or specify the data set prefix or data set mask. The data sets, data set prefixes, or data set masks specified in this panel may require that the Products Started Task have WRITE and/or greater access. If data set prefixes or data set masks are used, ensure that any data sets not associated with the product are deleted. Review the contents of the CSFPRMxx member in the data set identified in the Product Configuration panel. The entries for **CKDSN** and **PKDSN** specify the data sets for this group.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
              IBM Integrated Crypto Service Facility (ICSF)
SRRMPROD                                         Version: v.rr
Command ==>                                     Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the data sets and/or data set mask/prefix of the product STC
  data sets.  They are identified in the CSFPRMxx member.
=====
  Data set names and/or Data set prefixes          Volume
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and return to Product List.
Enter	Refresh panel list.
<a href="#">Help/PF1</a>	Display data set names and/or data set Prefixes Help.

Return to [Product List table](#).



### MQSeries/Websphere MQ Panels

#### Subsystem Identifier

The following panel appears for any product that requires a list of subsystem identifiers be specified for the product. For MQSeries/Websphere MQ the subsystem identifier is used in the STC JCL Location to identify the STC member names.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
                      MQSeries/Websphere MQ
SRRMPROD                                     Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the SubSystem Identifier for all occurrences of this product.

=====
  SSID
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to STC JCL Location.
Enter	Refresh panel list.

Return to [Product List table](#).

**STC JCL Location**

The following panel appears for MQSeries/Websphere MQ. Specify the member pair (MSTR and CHIN) and data set location of each MQSeries/Websphere MQ on this system. The data set can specify the actual or an alias of the data set. **Note:** The xxxx specified below is replaced by the subsystem identifier(s) specified in the Subsystem Identifier panel.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 2 of 2
                    MQSeries/Websphere MQ
SRRMPROD                                     Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information

Enter the Userid of the STC or batch job for this product.
Specify the data sets that contain the JCL for the MSTR and CHIN procedures.
=====
UserId      Member      Data set that contains the member JCL
-----
            xxxxCHIN   _____
            xxxxMSTR   _____
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and return to Product List.
Enter	Refresh panel list.

Return to [Product List table](#).

**NC-PASS Panels**

**STC JCL Location**

The following panel appears for NC-PASS. Specify the member and data set location of NC-PASS STC on this system. The data set can specify the actual or an alias of the data set.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
                                NC-PASS
SRRMPROD                               Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information

  Enter the Userid of the STC or batch job for this product.
  Enter the member and data set that contains the JCL for this product.
=====
UserId   Member   Data set that contains the member JCL
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Product Install data sets.
<a href="#">Enter</a>	Save information and continue to Product Install data sets.

Return to [Product List table](#).

### Product Install Data Sets

The following panel appears for any product that requests a list of data sets for the product. Specify the actual or alias of the data set or specify the data set prefix or data set mask. If data set prefixes or data set masks are used, ensure that any data sets not associated with the product are deleted.

```

----- Security Readiness Review Self-Audit ---- Row 1 to 1 of 1
                        NC-PASS
SRRMPROD                                     Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the data sets and/or data set mask/prefix of the product installation
  data sets.
=====
  Data set names and/or Data set prefixes          Volume
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Product STC data sets.
Enter	Refresh panel list.
<a href="#">Help/PF1</a>	Display data set names and/or data set Prefixes Help.

Return to [Product List table](#).

**Product STC Data Sets**

The following panel appears for any product that requests a list of data sets for the product. Specify the actual or alias of the data set or specify the data set prefix or data set mask. The data sets, data set prefixes, or data set masks specified in this panel may require that the Products Started Task have WRITE and/or greater access. If data set prefixes or data set masks are used, ensure that any data sets not associated with the product are deleted.

```

----- Security Readiness Review Self-Audit ---- Row 1 to 1 of 1
                          NC-PASS
SRRMPROD                                     Version: v.rr
Command ==>>> _____ Scroll ==>>> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the data sets and/or data set mask/prefix of the product STC
  data sets.
=====
  Data set names and/or Data set prefixes          Volume
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and return to Product List.
Enter	Refresh panel list.
<a href="#">Help/PF1</a>	Display data set names and/or data set Prefixes Help.

Return to [Product List table](#).

### Tivoli Netview Panels

#### STC JCL Location

The following panel appears for Tivoli Netview. Specify the member and data set location of each Tivoli Netview STC on this system. The data set can specify the actual or an alias of the data set.

```

----- Security Readiness Review Self-Audit ---- Row 1 to 2 of 2
                    Tivoli Netview
SRRMPROD                                     Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information

  Enter the Userid of the STCs or batch jobs for this product.
  Enter the member and data set for the sub-products that are installed.
=====
Product   UserId   Member   Data set that contains the member JCL
CNMPROC   _____
CNMPSSI   _____
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Configuration Location panel.
<a href="#">Enter</a>	Save information and continue to Configuration Location panel.

Return to [Product List table](#).

### Configuration Location

The following panel appears for Tivoli Netview. Specify the member and data set location of the specified Tivoli Netview configuration. The data set can specify the actual or an alias of the data set.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 2 of 2
                    Tivoli Netview
SRRMPROD                                     Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
  Enter data set name that contains CxxSTYLE member for the Product
  configuration.

=====
Member   Data set that contains the configuration member
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Product Install data sets.
<a href="#">Enter</a>	Save information and continue to Product Install data sets.

Return to [Product List table](#).

**Keyword and Value**

The following panel appears for Tivoli Netview. Specify the member and data set location of the specified Tivoli Netview configuration. The data set can specify the actual or an alias of the data set.

----- Security Readiness Review Self-Audit ----- Row 1 to 2 of 2	
Tivoli NetView for z/OS	
SRRMPROD	Version: v.rr
Command ==>	Scroll ==> CSR
Commands: CANCEL - Exit without saving information	
EXIT/END/PF3 - Ends and saves information	
Enter the Value for each Keyword.	
=====	
Keyword	Value
DOMAIN	
NetID	
***** Bottom of data *****	

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Product Install data sets.
<a href="#">Enter</a>	Save information and continue to Product Install data sets.

Return to [Product List table](#).



### Product Install Data Sets

The following panel appears for any product that requests a list of data sets for the product. Specify the actual or alias of the data set or specify the data set prefix or data set mask. If data set prefixes or data set masks are used, ensure that any data sets not associated with the product are deleted.

```

----- Security Readiness Review Self-Audit ---- Row 1 to 1 of 1
                    Tivoli Netview
SRRMPROD                                     Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the data sets and/or data set mask/prefix of the product installation
  data sets.
=====
  Data set names and/or Data set prefixes          Volume
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Product STC data sets.
Enter	Refresh panel list.
<a href="#">Help/PF1</a>	Display data set names and/or data set Prefixes Help.

Return to [Product List table](#).

### Product STC Data Sets

The following panel appears for any product that requests a list of data sets for the product. Specify the actual or alias of the data set or specify the data set prefix or data set mask. The data sets, data set prefixes, or data set masks specified in this panel may require that the Products Started Task have WRITE and/or greater access. If data set prefixes or data set masks are used, ensure that any data sets not associated with the product are deleted.

```

----- Security Readiness Review Self-Audit ---- Row 1 to 1 of 1
                    Tivoli Netview
SRRMPROD
Command ==>>> _____ Version: v.rr
Commands:  CANCEL - Exit without saving information
           EXIT/END/PF3 - Ends and saves information
Line command:  D - Delete entry
Enter the data sets and/or data set mask/prefix of the product STC
data sets.
=====
Data set names and/or Data set prefixes          Volume
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and return to Product List.
Enter	Refresh panel list.
<a href="#">Help/PF1</a>	Display data set names and/or data set Prefixes Help.

Return to [Product List table](#).

### CA ROSCOE Panels

#### STC JCL Location

The following panel appears for CA ROSCOE. Specify the member and data set locations of all CA ROSCOE STCs on this system. The data set can specify the actual or an alias of the data set.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
                          CA ROSCOE
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the Userid of the STCs or batch jobs for this product.
  Enter the members and data sets that contain the JCL for this product.
=====
  UserId      Member      Data set that contains the member JCL
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Resource Identification panel.
Enter	Refresh panel list.

Return to [Product List table](#).

**Resource Identification**

One of the following panels will be displayed depending on the ACP running on the system. The following are links to each ACP panel for CA ROSCOE.

- [ACF2](#)
- [RACF](#)
- [TSS](#)

**ACF2**

Enter the Resource Type used by the CA ROSCOE product.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
                                CA ROSCOE
SRRMPROD                                     Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information

Enter the Resource Type for the product.

=====
Member   Resource Type
xxxxxxx
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Configuration Location panel.
Enter	Refresh panel list.

Return to [Product List table](#).

**RACF**

Enter the Resource Class used by the CA ROSCOE product.

```

----- Security Readiness Review Self-Audit ---- Row 1 to 1 of 1
                          CA ROSCOE
SRRMPROD                                     Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information

Enter the Resource Class for the product.

=====
Member   Resource Class
xxxxxxx _____
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Configuration Location panel.
Enter	Refresh panel list.

Return to [Product List table](#).

**TSS**

Enter the Resource Class used by the CA ROSCOE product.

```

----- Security Readiness Review Self-Audit ---- Row 1 to 1 of 1
              CA ROSCOE
SRRMPROD
Command ==> _____ Version: v.rr
Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information

  Enter the Resource Class for the product.

=====
Member   Resource Class
xxxxxxx _____
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Configuration Location panel.
Enter	Refresh panel list.

Return to [Product List table](#).

### Configuration Location

The following panel appears for CA ROSCOE. Specify the member and data set locations of each CA ROSCOE Product on this system. The data set can specify the actual or an alias of the data set.

```

----- Security Readiness Review Self-Audit ---- Row 1 to 2 of 2
                                CA ROSCOE
SRRMPROD                               Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
              EXIT/END/PF3 - Ends and saves information
  Enter member and data set name that contains the product configuration.

=====
STC/JOB  Member   Data set that contains the configuration member
xxxxxxx  _____
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Product Install data sets.
Enter	Refresh panel list.

Return to [Product List table](#).

### Product Install Data Sets

The following panel appears for any product that requests a list of data sets for the product. Specify the actual or alias of the data set or specify the data set prefix or data set mask. If data set prefixes or data set masks are used, ensure that any data sets not associated with the product are deleted.

```

----- Security Readiness Review Self-Audit ---- Row 1 to 1 of 1
                          CA ROSCOE
SRRMPROD                                     Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the data sets and/or data set mask/prefix of the product installation
  data sets.
=====
  Data set names and/or Data set prefixes          Volume
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Product STC data sets.
Enter	Refresh panel list.
<a href="#">Help/PF1</a>	Display data set names and/or data set Prefixes Help.

Return to [Product List table](#).



### Product STC Data Sets

The following panel appears for any product that requests a list of data sets for the product. Specify the actual or alias of the data set or specify the data set prefix or data set mask. The data sets, data set prefixes, or data set masks specified in this panel may require that the Products Started Task have WRITE and/or greater access. If data set prefixes or data set masks are used, ensure that any data sets not associated with the product are deleted. The data sets in this group are the data sets identified in the ROSACTxx, ROSLIBxx, and SYSAWSx DD statements in the ROSCOE JCL.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
                          CA ROSCOE
SRRMPROD                                     Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
Line command: D - Delete entry
Enter the data sets and/or data set mask/prefix of the product STC
data sets.
=====
Data set names and/or Data set prefixes          Volume
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and return to Product List.
Enter	Refresh panel list.
<a href="#">Help/PF1</a>	Display data set names and/or data set Prefixes Help.

Return to [Product List table](#).

**SDSF Panels**

**STC JCL Location**

The following panel appears for SDSF. Specify the member and data set location of each SDSF on this system. Additional SDSF STCs can be entered on the blank entry line or by overtyping the new SDSF STCs on any or all filled lines. The data set can specify the actual or an alias of the data set.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
              System Display and Search Facility
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
              EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the Userid of the STCs or batch jobs for this product.
  Enter the members and data sets that contain the JCL for this product.
=====
  UserId      Member      Data set that contains the member JCL
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Product Install data sets.
Enter	Refresh panel list.

Return to [Product List table](#).

### Product Install Data Sets

The following panel appears for any product that requests a list of data sets for the product. Specify the actual or alias of the data set or specify the data set prefix or data set mask. If data set prefixes or data set masks are used, ensure that any data sets not associated with the product are deleted.

```

----- Security Readiness Review Self-Audit ---- Row 1 to 1 of 1
              System Display and Search Facility
SRRMPROD                                         Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
              EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the data sets and/or data set mask/prefix of the product installation
  data sets.
=====
  Data set names and/or Data set prefixes          Volume
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and return to Product List.
Enter	Refresh panel list.
<a href="#">Help/PF1</a>	Display data set names and/or data set Prefixes Help.

Return to [Product List table](#).

### SRRAUDIT Panels

#### Product Install Data Sets

The following panel appears for any product that requests a list of data sets for the product. Specify the actual or alias of the data set or specify the data set prefix or data set mask. If data set prefixes or data set masks are used, ensure that any data sets not associated with the product are deleted.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
                    SRRAUDIT Process
SRRMPROD                                     Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the data sets and/or data set mask/prefix of the product installation
  data sets.
=====
  Data set names and/or Data set prefixes          Volume
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Product User data sets.
Enter	Refresh panel list.
<a href="#">Help/PF1</a>	Display data set names and/or data set Prefixes Help.

Return to [Product List table](#).

### Product User Data Sets

The following panel appears for any product that requests a list of data sets for the product. Specify the actual or alias of the data set or specify the data set prefix or data set mask. If data set prefixes or data set masks are used, ensure that any data sets not associated with the product are deleted.

```

----- Security Readiness Review Self-Audit ---- Row 1 to 1 of 1
                SRRAUDIT Process
SRRMPROD                                           Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the data sets and/or data set mask/prefix of the product user
  data sets.
=====
  Data set names and/or Data set prefixes          Volume
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and return to Product List.
Enter	Refresh panel list.
<a href="#">Help/PF1</a>	Display data set names and/or data set Prefixes Help.

Return to [Product List table](#).

### Tivoli Asset Discovery for z/OS (TADz) Panels

#### STC/Batch JCL Location

The following panel appears for TADz. Specify the member and data set location of TADz STC and Batch JCL on this system. The data set can specify the actual or an alias of the data set.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
              Tivoli Asset Discovery for z/OS (TADz)
SRRMPROD                                           Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the Userid of the STCs or batch jobs for this product.
  Enter the members and data sets that contain the JCL for this product.
=====
  UserId      Member      Data set that contains the member JCL
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Product Install data sets.
Enter	Refresh panel list.

Return to [Product List table](#).

### Product Install Data Sets

The following panel appears for any product that requests a list of data sets for the product. Specify the actual or alias of the data set or specify the data set prefix or data set mask. If data set prefixes or data set masks are used, ensure that any data sets not associated with the product are deleted.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
              Tivoli Asset Discovery for z/OS (TADz)
SRRMPROD                                         Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
              EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the data sets and/or data set mask/prefix of the product installation
  data sets.
=====
  Data set names and/or Data set prefixes          Volume
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Product STC data sets.
Enter	Refresh panel list.
<a href="#">Help/PF1</a>	Display data set names and/or data set Prefixes Help.

Return to [Product List table](#).

### Product STC Data Sets

The following panel appears for any product that requests a list of data sets for the product. Specify the actual or alias of the data set or specify the data set prefix or data set mask. The data sets, data set prefixes, or data set masks specified in this panel may require that the Products Started Task have WRITE and/or greater access. If data set prefixes or data set masks are used, ensure that any data sets not associated with the product are deleted.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
              Tivoli Asset Discovery for z/OS (TADz)
SRRMPROD                                           Version: v.rr
Command ==>>> _____ Scroll ==>>> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the data sets and/or data set mask/prefix of the product STC
  data sets.
=====
  Data set names and/or Data set prefixes           Volume
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and return to Product List.
Enter	Refresh panel list.
<a href="#">Help/PF1</a>	Display data set names and/or data set Prefixes Help.

Return to [Product List table](#).



### Transparent Data Migration Facility (TDMF) Panels

#### All Product Data Sets

The following panel appears for any product that requests a list of data sets for the product. Specify the actual or alias of the data set or specify the data set prefix or data set mask. If data set prefixes or data set masks are used, ensure that any data sets not associated with the product are deleted.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
              Transparent Data Migration Facility (TDMF)
SRRMPROD                                         Version: v.rr
Command ==>> _____ Scroll ==>> CSR
  Commands:  CANCEL - Exit without saving information
              EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the data sets and/or data set mask/prefix of all of the product
  data sets.
=====
  Data set names and/or Data set prefixes          Volume
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and return to Product List.
Enter	Refresh panel list.
<a href="#">Help/PF1</a>	Display data set names and/or data set Prefixes Help.

Return to [Product List table](#).

### Vanguard Security Solutions (VSS) Panels

#### All Product Data Sets

The following panel appears for any product that requests a list of data sets for the product. Specify the actual or alias of the data set or specify the data set prefix or data set mask. If data set prefixes or data set masks are used, ensure that any data sets not associated with the product are deleted.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
              Vanguard Security Solutions (VSS)
SRRMPROD                                         Version: v.rr
Command ==>>> _____ Scroll ==>>> CSR
  Commands:  CANCEL - Exit without saving information
              EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the data sets and/or data set mask/prefix of all of the product
  data sets.
=====
  Data set names and/or Data set prefixes          Volume
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Product User data sets.
Enter	Refresh panel list.
<a href="#">Help/PF1</a>	Display data set names and/or data set Prefixes Help.

Return to [Product List table](#).

### Product User Data Sets

The following panel appears for any product that requests a list of data sets for the product. Specify the actual or alias of the data set or specify the data set prefix or data set mask. If data set prefixes or data set masks are used, ensure that any data sets not associated with the product are deleted.

```

----- Security Readiness Review Self-Audit ---- Row 1 to 1 of 1
              Vanguard Security Solutions (VSS)
SRRMPROD                                     Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
              EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the data sets and/or data set mask/prefix of the product user
  data sets.
=====
  Data set names and/or Data set prefixes          Volume
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and return to Product List.
Enter	Refresh panel list.
<a href="#">Help/PF1</a>	Display data set names and/or data set Prefixes Help.

Return to [Product List table](#).

### VTAM Panels

#### STC JCL Location

The following panel appears for VTAM. Specify the member and data set location of VTAM STC on this system. The data set can specify the actual or an alias of the data set.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
                        VTAM
SRRMPROD                                     Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information

  Enter the Userid of the STC or batch job for this product.
  Enter the member and data set that contains the JCL for this product.
=====
UserId      Member      Data set that contains the member JCL
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and return to Product List.
<a href="#">Enter</a>	Save information and return to Product List.

Return to [Product List table](#).

### All Product Data Sets

The following panel appears for any product that requests a list of data sets for the product. Specify the actual or alias of the data set or specify the data set prefix or data set mask. If data set prefixes or data set masks are used, ensure that any data sets not associated with the product are deleted.

```

----- Security Readiness Review Self-Audit ---- Row 1 to 1 of 1
                        VTAM
SRRMPROD                                     Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the data sets and/or data set mask/prefix of all of the product
  data sets.
=====
  Data set names and/or Data set prefixes          Volume
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and return to Product List.
Enter	Refresh panel list.
<a href="#">Help/PF1</a>	Display data set names and/or data set Prefixes Help.

Return to [Product List table](#).

### CA VTape Panels

#### Subsystem Identifier

The following panel appears for any product that requires a list of subsystem identifiers be specified for the product. Use the value specified for the SVTS variable specified in the SVTS started task proclib member.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
                          CA VTape
SRRMPROD                                     Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the SubSystem Identifier for all occurrences of this product.

=====
  SSID
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to STC JCL Location.
Enter	Refresh panel list.

Return to [Product List table](#).

**STC JCL Location**

The following panel appears for CA VTape. Specify the member and data set location of each CA VTape Product STC and/or Batch job on this system. The data set can specify the actual or an alias of the data set.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
                                CA VTape
SRRMPROD                                Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the Userid of the STCs or batch jobs for this product.
  Enter the members and data sets that contain the JCL for this product.
=====
  UserId      Member      Data set that contains the member JCL
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Product Install data sets.
Enter	Refresh panel list.

Return to [Product List table](#).

### Product Install Data Sets

The following panel appears for any product that requests a list of data sets for the product. Specify the actual or alias of the data set or specify the data set prefix or data set mask. If data set prefixes or data set masks are used, ensure that any data sets not associated with the product are deleted.

```

----- Security Readiness Review Self-Audit ---- Row 1 to 1 of 1
                        CA VTAPE
SRRMPROD                                     Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the data sets and/or data set mask/prefix of the product installation
  data sets.
=====
  Data set names and/or Data set prefixes          Volume
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and continue to Product STC data sets.
Enter	Refresh panel list.
<a href="#">Help/PF1</a>	Display data set names and/or data set Prefixes Help.

Return to [Product List table](#).



### Product STC Data Sets

The following panel appears for any product that requests a list of data sets for the product. Specify the actual or alias of the data set or specify the data set prefix or data set mask. The data sets, data set prefixes, or data set masks specified in this panel may require that the Products Started Task have WRITE and/or greater access. If data set prefixes or data set masks are used, ensure that any data sets not associated with the product are deleted.

```

----- Security Readiness Review Self-Audit ---- Row 1 to 1 of 1
                          CA VTape
SRRMPROD                                     Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the data sets and/or data set mask/prefix of the product STC
  data sets.
=====
  Data set names and/or Data set prefixes          Volume
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and return to Product List.
Enter	Refresh panel list.
<a href="#">Help/PF1</a>	Display data set names and/or data set Prefixes Help.

Return to [Product List table](#).

## HTTP/Web Application Server Panels

### STC JCL Location

The following panel appears for HTTP/Web Application Server. Specify the member and data set location of each HTTP/Web Application Server on this system. Additional HTTP/Web Application Server STCs can be entered on the blank entry line or by overtyping the new HTTP/Web Application Server STCs on any or all filled lines. The data set can specify the actual or an alias of the data set.

```

----- Security Readiness Review Self-Audit ---- Row 1 to 1 of 1
              HTTP/Web Application Server
SRRMPROD                                           Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
              EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the Userid of the STCs or batch jobs for this product.
  Enter the members and data sets that contain the JCL for this product.
=====
  UserId   Member   Data set that contains the member JCL
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Product List without saving information.
<a href="#">End/Exit/PF3</a>	Save information and return to Product List.
Enter	Refresh panel list.

Return to [Product List table](#).

### Vulnerability Questions

This function is used to provide the evaluation of vulnerabilities that require Yes/No answers. The following panel is an extended list of the Vulnerability Questions currently collected.

**Note:** It is recommended that the ISSO review the questions for each of the following STIG IDs.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 9 of 9
                    Vulnerability Questions
SRRMPROD
Command ==> _____ Version: v.rr
                        Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
  Line command:  Y - Yes
                N - No
  Y/N column:  Y=Yes, N=No, Y?=Yes Missing information
-----
  STIG Id   Y/N Vulnerability Question
  _ AAMV0012   Is unsupported system software install and active on the
                system?
  _ AAMV0400   Is there an automated process in place to collect and
                retain SMF data for this system?
  _ ACP00110   Does the System LINKLIST contain application and/or
                user loadlibs?
  _ ACP00190   Are there SMF dump/backup datasets on this system?
  _ ACP00210   Are there system DASD backup datasets on this system?
  _ ACP00270   Does software product require access to dynamic LPA updates?
                It must be validated with the appropriate STIG or SRG and
                receive documented and filed authorization from the site ISSM.
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Application Option Menu without saving information.
<a href="#">End/Exit/PF3</a>	Save information and return to Application Option Menu.
Enter	Refresh panel list.

Line Option	Description
N	Specifies a NO response to the question or request.
Y	Specifies a YES response to the question or request.

At this screen, you can specify (N or Y) for each question or request for information line.

The following is a table of STIG IDs for which additional panels will appear for possible request for information when specifying (Y) for the question or request:

UNCLASSIFIED

<b>STID ID</b>	<b>Vulnerability Question</b>	<b>Panels</b>
AAMV0012	Is unsupported system software install and active on the system?	<a href="#">AAMV0012</a>
ACP00110	Does the System LINKLIST contain application and/or user loadlibs?	<a href="#">ACP00110</a>
ACP00190	Provide a list of SMF dump/backup data sets.	<a href="#">ACP00190</a>
ACP00210	Provide a list of system DASD backup data sets.	<a href="#">ACP00210</a>
ACP00270	Provide a list of Start Task users that require access to CSVDYLPA.ADD and/or CSVDYLPA.DELETE resources.	<a href="#">ACP00270</a>

**AAMV0012**

The following panel appears for STIG ID AAMV0012. Specify the list of Unsupported System Software and version that is available on the system

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
                        AAMV0012
SRRMPROD                                     Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
  Question:  Is unsupported system software install and active on the
             system?

  Line command:  D - Delete entry
  Enter the Product and Version of unsupported software.
-----
  Product Name          Version
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Vulnerability Questions.
<a href="#">End/Exit/PF3</a>	Save information and return to Vulnerability Questions.
Enter	Refresh panel list.

Return to [Vulnerability Questions table](#).

**ACP00110**

The following panel appears for STIG ID ACP00110. Specify the data set names of application and/or user LINKLIST data sets. Specify the actual or alias of the data set or specify the data set prefix or data set mask. If data set prefixes or data set masks are used, ensure that any data sets not associated with application and/or user LINKLIST data sets are deleted.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
                        ACP00110
SRRMPROD                                     Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
  Question:  Does the System LINKLIST contain application and/or
             user datasets?

  Line command:  D - Delete entry
  Enter the data set names of application and/or user LINKLIST loadlibs.
=====
  Data set names
_____
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Vulnerability Questions without saving information.
<a href="#">End/Exit/PF3</a>	Save information and return to Vulnerability Questions.
Enter	Refresh panel list.
<a href="#">Help/PF1</a>	Display data set names and/or data set Prefixes Help.

Return to [Vulnerability Questions table](#).

**ACP00190**

The following panel appears for STIG ID ACP00190. Specify the list of SMF dump/backup data sets. Specify the actual or alias of the data set or specify the data set prefix or data set mask. If data set prefixes or data set masks are used, ensure that any data sets not associated with the SMF dump/backup data sets are deleted.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
                        ACP00190
SRRMPROD                                     Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
  Request:   Provide a list of SMF dump/backup datasets.

  Line command:  D - Delete entry
  Enter the data sets and/or data set mask/prefix for this request.
=====
  Data set names and/or Data set prefixes          Volume
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Vulnerability Questions without saving information.
<a href="#">End/Exit/PF3</a>	Save information and return to Vulnerability Questions.
Enter	Refresh panel list.
<a href="#">Help/PF1</a>	Display data set names and/or data set Prefixes Help.

Return to [Vulnerability Questions table](#).

**ACP00210**

The following panel appears for STIG ID ACP00210. Specify the list of DASD backup data sets. Specify the actual or alias of the data set or specify the data set prefix or data set mask. If data set prefixes or data set masks are used, ensure that any data sets not associated with DASD backup are deleted.

```

----- Security Readiness Review Self-Audit ----- Row 1 to 1 of 1
                        ACP00210
SRRMPROD                                     Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
Request: Provide a list of system DASD backup data sets.

  Line command:  D - Delete entry
Enter the data sets and/or data set mask/prefix for this request.
=====
  Data set names and/or Data set prefixes          Volume
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Vulnerability Questions without saving information.
<a href="#">End/Exit/PF3</a>	Save information and return to Vulnerability Questions.
Enter	Refresh panel list.
<a href="#">Help/PF1</a>	Display data set names and/or data set Prefixes Help.

Return to [Vulnerability Questions table](#).



**ACP00270**

The following panel appears for STIG ID ACP00270. Specify the list of Started Task Users that require access to CSVDYLPA.ADD and/or CSVDYLPA.DELETE resources. Specify the UserId, member, Resource, and data set location of STCs on this system. The values for the Resource column are “A” for CSVDYLPA.ADD, “D” for CSVDYLPA.DELETE, and space for both resources. The data set can specify the actual or an alias of the data set.

```

----- Security Readiness Review Self-Audit ---- Row 1 to 1 of 1
                        ACP00270
SRRMPROD                                     Version: v.rr
Command ==> _____ Scroll ==> CSR
  Commands:  CANCEL - Exit without saving information
             EXIT/END/PF3 - Ends and saves information
  Line command:  D - Delete entry
  Enter the Userid of the STCs that require access to the ACP00270 resource.
  Enter the members and data sets that contain the JCL.
  Resource values - A = CSVDYLPA.ADD, D = CSVDYLPA.DELETE, Space = Both

=====
  UserId   Member   Resource   Data set that contains the member JCL
-----
***** Bottom of data *****

```

Option	Description
<a href="#">Cancel</a>	Return to Vulnerability Questions without saving information.
<a href="#">End/Exit/PF3</a>	Save information and return to Vulnerability Questions.
Enter	Refresh panel list.

Return to [Vulnerability Questions table](#).